~~PART 6~~

Part -2B

GENERAL ELECTRICAL REQUIREMENTS

Table of Contents

Part ~~6~~2B -
GENERAL ELECTRICAL REQUIREMENTS

~~6~~2.1 Introduction 3
~~6~~2.2 General 3
~~6~~2.3 Equipment 3
~~6.4 Transformers 6~~
~~6.4.1 Applicable Standards 6~~
~~6.4.2 Features of Construction 6~~
~~6.4.3 Winding connections 7~~
~~6.4.4 Rating 7~~
~~6.4.5 Type of cooling 7~~
~~6.4.6 Impedance and losses 8~~
~~6.4.7 Performance requirements 8~~
~~6.4.8 Tap Changer 8~~
~~6.4.9 Fittings and Accessories 13~~
~~6.4.10 Cable Terminations 14~~
~~6.4.11 Tolerance on Losses 14~~
~~6.4.12 Rejection 15~~
~~6.4.13 Drawings and Data 15~~
~~6.5 11 kV Metal Enclosed Switchboards & Switchgears 15~~
~~6.5.1 Applicable Standards 15~~
~~6.5.2 Constructional Features 16~~
~~6.5.3 Circuit Breaker 18~~
~~6.5.4 Operating Mechanism Control 18~~
~~6.5.5 Safety Interlocks And Features 19~~
~~6.5.6 Earthing 20~~
~~6.5.7 Circuit / Busbar Earthing Facility 20~~
~~6.5.8 Annunciators 21~~
~~6.5.9 Indicating Instruments & Meters 21~~
~~6.5.10 Control and Selector Switches 22~~
~~6.5.11 Indicating Lamps / Pilot Lamps 23~~
~~6.5.12 Push Buttons 23~~
~~6.5.13 Space Heaters 24~~
~~6.5.14 Cubicle Lighting / Receptacle 24~~

~~6.5.15 Power and Control Cable Termination 24~~
~~6.5.16 Wiring For Control and Protective Circuits 24~~
~~6.5.17 Termination and Ferrules 25~~
~~6.5.18 Control Wiring Terminal Blocks 25~~
~~6.5.19 BusBars 26~~
~~6.5.20 Current & Voltage Transformers 26~~
~~6.5.21 Relays 27~~
~~6.5.22 Energy monitoring and Management 28~~
~~6.5.23 I / O & Other Data for Instrumentation, Control & Automation System 28~~
~~6.5.24 Drawings and Data 28~~
2.4~~6.6~~ 415 V Metal Enclosed Switchgears (PCC) / MCC 4
2.4.1~~6.6.1~~ Applicable Standards 4
2.4~~6.6~~.2 Features of Construction 5
2.4.~~6.6.~~3 Air Circuit Breaker (ACB) 6
2.4.~~6.6.~~4 Moulded Case Circuit Breaker (MCCB) 7
2.4.~~6.6.~~5 Switches and Fuses 7
~~6.6~~2.4.6 Miniature Circuit Breaker (MCB) 8
~~6.6~~2.4.7 Contactors 8
~~6.6~~2.4.8 Current Transformers 9
~~6.6~~2.4.9 Voltage Transformers 9
~~6.6~~2.4.10 Indicating Instruments & Meters 9
~~6.6~~2.4.11 Indicating Lamps 10
~~6.6~~2.4.12 Push Buttons 10
~~6.6~~2.4.13 Space Heaters 10
~~6.6~~2.4.14 Safety Arrangements 10

6.62.4.15 Earthing of Switchboards / Panels 10
6.62.4.16 Internal Wiring 11
6.6.17 I / O & Other Data for Instrumentation, Control & Automation System 37
2.46.6.18 Drawing and Data 11
6.7 415 V Power capacitor and control panel 37
6.7.1 Applicable Standards 37
6.7.2 Design Features 38
6.7.3 Power Capacitor and Control Panel 39
6.7.4 Drawings and Data 40
6.8 Diesel Standby Generator 40
6.8.1 Applicable Standards 40
6.8.2 General Requirements 41
6.8.3 Diesel Generating Set Automatic Control 42
6.8.4 Alternator for Diesel Generating Set 43
6.8.5 Diesel Engine for Generating Set 44
6.8.6 Diesel Generator Control Panel : 46
6.8.7 Synchronising Panel 47
6.8.8 Acoustic Enclosure 47
6.8.9 Bulk Fuel Storage Tanks 48
6.8.10 Drawings 48
6.9 Battery, Battery Charger and D.C Distribution Board 49
6.9.1 Nickel – Cadmium Battery 49
6.9.2 Battery Charger and D.C. Distribution Board 51
2.56.10 Variable Frequency Drives 11
6.102.5.1 Applicable Standards 11
6.102.5.2 Configuration 12
6.102.5..3 Inverter 12
6.102.5.4 Control Requirements 14
6.102.5.5 Protection 14

6.102.5.6 Cooling Of Power Converters 15
6.102.5.7 Switching Devices 15
6.102.5.8 Constructional Features 15
6.112.6 Non-Segregated Bus Duct 19
6.112.6.1 Bus Enclosure 20
6.112.6.2 Bus Conductor 21
6.112.6.3 Phase Barriers 22
6.112.6.4 Bus Support Insulators 22
6.112.6.5 Wall Frame Assembly And Seal – off Bushing 22
6.112.6.6 Bus Duct Supports 232
6.122.7 Cables : HV, LV Power and Control 23
6.122.7.1 Applicable Standards 24
6.122.7.2 Features of Construction 24
6.122.7.3 Cable Rating 25
6.122.7..4 Cable Colours 265
6.122.7.5 Cable Conductors 26
6.122.7.6 Cable Numbering 26
6.122.7.7 Cable Drums 276
6.122.7.8 Cable Installation 27
6.122.7.9 Cable Terminations and Joints 34

6.122.7.10 Drawings and Data
376
6.132.8 Cable Carrier System
376
6.132.8.1 General
376
6.132.8.2 Applicable Standards
37
6.132.8.3 Cable Racks and Trays
387
6.132.8.4 Galvanising
387
6.132.8.5 Drawings and Data
38
6.14 Lighting System 88
6.14.1 General Requirements 88
6.14.2 Applicable Standards 89
6.14.3 Lighting Fixtures (Luminaires) 91
6.14.4 Decorative Luminaires 93
6.14.5 Industrial Luminaires 94
6.14.6 Flood Light Luminaire 95
6.14.7 Outdoor Lantern Luminaires 96
6.14.8 Street Lighting Luminaires 96
6.14.9 Accessories for Luminaires 98
6.14.10 Lighting System Equipment 100
2.96.15 Earthing and Lightning Protection System
398
6.152.9.1 General
398
6.152.9.2 Applicable Standards
39
6.152.9.3 Earthing Conductor
4039
6.152.9.4 Main Equipotential Bonding Conductor
410
6.152.9.5 Circuit Protective Conductors
421
6.152.9.6 Instrumentation Earth
433

~~6.15~~2.9.7 Galvanising 43
~~6.16~~2.10 Preferred Makes/ Manufacturers: 4~~4~~3

~~PART 6~~

GENERAL ELECTRICAL REQUIREMENTS

2.1 Introduction

The general requirements include design, manufacture~~–~~,_inspection and testing at works, supply and delivery at site, unloading and storing the equipment at site of installation, testing and commissioning of the equipment at site~~ listed below under clause no. 6.3.~~. All the electrical and instrumentation equipments to be supplied under this contract have to be of reputed ~~-~~makes. The equipment of those manufacturers, who have sufficient proven experience of manufacturing the respective equipment of similar capacity, shall be considered. The respective equipment should have been manufactured, supplied, installed, ~~C~~ccommissioned successfully and should be running satisfactorily since at least~~atleast~~ last 5 years continuously. Certificates from the end users, regarding their satisfactory ~~P~~pperformances, shall have to be submitted in this regard.

Particular requirements of all electrical equipments are covered under 'Part ~~1~~22: Particular Requirements – Electrical' of this Specification. Various equipment /items shall conform to latest applicable standards specified. In

case of ~~C~~conflict between standards and this specification, this specification shall govern.

2.2 General

For uniformity of appearance all switchgear and control panels shall have a common appearance and colour.
In order to reduce the spares holding to a minimum electrical components of a similar type and purpose used throughout the Works, unless it can be shown by the Contractor to be impractical , shall be of the same manufacturer and type / series.

2.3 Equipment

(a) ~~Transformers~~
~~(b) 11 kV Metal enclosed switchboards & switchgears~~
~~(c)~~ 415 V metal enclosed switchgears (PCC) /MCC
(d) ~~415 V Power capacitor and control panel~~
~~(e) Diesel Standby Generator with AMF Control Panel and Synchronizing panel~~
~~(f) Battery, battery charger and DC Distribution Board~~
~~(g)~~ Variable Frequency Drives
(h) Non Segregated Bus Duct
(i) Power & control cables
(j) Cable carrier system
(k) ~~Lighting system~~
~~(l)~~ Earthing and lightning protection systems

~~**5 Transformers**~~
~~**6**~~
~~**7 Applicable Standards**~~
~~**8**~~
~~**9 The transformers shall conform to the latest applicable standards specified below :**~~
~~**10**~~

~~Power Transformer~~	~~IS:2026/BS:171/ IEC:60076~~
~~Fittings and Accessories~~	~~IS:3639~~
~~Auxiliary Transformer~~	~~IS:1180~~
~~Loading of oil immersed transformer~~	~~IS:6600/BS:CP.1010~~

	/IEC:60354
Oil	IS:335/BS 148/IEC:60296
Bushings for > 1000V, AC	IS:2099/BS:223/ IEC:60137
Bushings for ≤ 1000V, AC	IS:7421
Degree of Protection	IS:13947 (Part 1) / IEC:60947-1
Buchholz Relay	IS:3637
Electrical insulation classified by thermal stability	IS 1271/BS:2757/IEC:60085
Climate Proofing	BS:CP1014
Code of Practise for selection ,installation and Maintenance of transformers	IS - 10028
Manual on Transformers	CBIP Publication No.295

10.1 Features of Construction

10.2

10.3 The transformer tank shall be made from high-grade sheet steel, suitably reinforced by stiffeners made of structural steel sections. All seams, flanges, lifting lugs, braces, and other parts attached to the tank shall be welded. The interior of the tank shall be cleaned by sand blasting and painted with two coats of heat resistant, oil insoluble paint. Adequately sized manholes shall be provided for ease of inspection and maintenance. Steel bolts and nuts exposed to atmosphere, shall be galvanised. The tank cover shall be removable and shall be suitably sloped so that it does not retain rainwater.

Lifting lugs and eyebolts shall be so located that a safe clearance is obtained without the use of a spreader, between the sling and transformer bushings.

Transformers shall be provided with fixed type radiators. Fins of the radiators shall not have sharp edges and shall be rounded in shape.

~~The transformer core shall be constructed from high grade, non ageing, cold rolled, grain oriented, silicon steel laminations. The steel laminations shall be of "core" type. Each lamination shall be coated with insulation which is unaffected by the temperature attained by the transformer during service. Core laminations shall be annealed and burrs removed after cutting. Cut edges shall be insulated. The framework and clamping arrangements of core and coil shall be securely earthed inside the tank by a copper strap connection to the tank.~~

~~Windings shall be of insulated copper wire or copper strip. Windings and insulation shall be so arranged that free circulation of oil is possible between coils, between windings, and between winding and core. The windings shall be fully shrunk under vacuum before assembly. High voltage end windings shall be suitably braced to withstand short circuit stresses and stresses caused up by surges.~~

~~The sequence and orientation of HV/LV side phase and neutral bushings shall be as specified in the latest edition of relevant IS.~~

~~Transformer shall operate without injurious heating at the rated KVA and at any voltage up to + 10 % of the rated voltage of any tap. Transformer shall be designed for 110 % continuous over fluxing withstand capability.~~

~~Winding connections~~

~~Windings shall be of HV :Delta & LV : Star , vector group Dyn 11.~~

~~Rating~~

~~The rating of transformers shall be as per standard ratings shown in IS 2026 / CBIP Publication.295.~~

~~Type of cooling~~

~~The transformers shall be oil immersed with natural oil circulation, type ONAN.~~

~~Impedance and losses~~

The percentage impedance , no load & load losses shall be as per IS 2026 & CBIP Publication.295 subject to tolerances as per IS 2026.

Performance requirements

The transformers shall be suitable for operation without danger on to any particular tapping at the rated kVA provided that the voltage does not vary by more than ± 10 % of the voltage corresponding to the tapping .

The transformers shall be suitable for continuous operation with a frequency variation of ± 5 % of rated frequency, combined voltage and frequency variation should not exceed 10 %.

All transformers shall be capable of withstanding external short circuit without damage as per IS 2026.

The transformers shall be capable of continuous operation in accordance with relevant IS for loading of oil immersed transformers.

The neutral terminal of star windings shall be designed for the highest over current that can flow through this terminal.

The temperature rise of oil & windings over the specified ambient temperature shall not exceed the limits given below with air as cooling medium.

Top oil (measured by thermometer) : 50° C
Winding (measured by resistance) : 55° C

(a) Noise level of transformers shall be less than 80 dB.
(b)
(c)
(d)
(e)
(f) Tap Changer
(g)
(h) For transformer of rating less than or equal to 500 kVA ,tap changing shall be carried out by means of an off circuit externally operated self positioning switch when the transformer is in de energised condition. Tappings shall be provided on the higher voltage winding for variation of HV voltage from plus 5% to

minus 10% in steps of 2.5%. For transformer of rating greater than 500 kVA . On load tap changer may be provided on HV side for variation HV voltage from plus 5% to minus 15% in steps of 1.25%.

(i)

(j) 6.4.8.1 On Load Tap Changing Gear for Transformer

(k)

(l) The OLTC gear shall be designed to complete successfully tap changes for the maximum current to which transformer can be loaded i.e., 150% of the rated current. Devices shall be incorporated to prevent tap change when the through current is in excess of the safe current that the tap changer can handle. The OLTC gear shall withstand through fault currents without injury.

(m)

(n) When a tap change has been commenced it shall be completed independently of the operation of the control relays and switches. Necessary safeguard shall be provided to allow for failure of auxiliary power supply or any other contingency which may result in the tap changer movement not being completed once it is commenced.

(o)

(p) Oil in compartments which contain the making and breaking contacts of the OLTC shall not mix with oil in other compartments of the OLTC or with transformer oil. Gases released from these compartments shall be conveyed by a pipe to a separate oil conservator or to a segregated compartment within the main transformer conservator. A Buchholz relay shall be installed in the above pipe. The conservator shall be provided with a prismatic oil level gauge.

(q)

(r) Oil, in compartments of OLTC which do not contain the make and break contacts, shall be maintained under conservator head by valved pipe connections. Any gas leaving these compartments, shall pass through the Buchholz relay before entering the conservator.

(s)

(t) Oil filled compartments shall be provided with filling plug, drain valve with plug, air release vent, oil sampling device, inspection opening with gasketed and bolted cover with lifting handles.

(u)

(v) OLTC driving mechanism and its associated control equipment (Local) shall be mounted in an outdoor, weather proof cabinet with IP 55 protection which shall include :

(w)

(x) Driving motor (415V, 3-phase, 50 Hz. AC squirrel cage).

(y)

(z) Motor starting contactor with thermal overload relays, isolating switch and HRC fuses.

(aa)

(bb) Duplicate sources of power supply with automatic changeover from the running source to the standby source and vice versa.

(cc)

(dd) Control switch : Raise/off/lower(spring return to normal type).

(ee)

(ff) Remote/local selector switch (maintained contact type).

~~(gg)~~

~~(hh) Mechanical tap position indicator showing rated tap voltage against each position and resettable maximum and minimum indicators.~~

~~(ii)~~

~~(jj) Limit switches to prevent motor over-travel in either direction and final mechanical stops.~~

~~(kk)~~

~~(ll) Brake or clutch to permit only one tap change at a time on manual operation.~~

~~(mm)~~

~~(nn) Emergency manual operating device (hand crank or hand wheel).~~

~~(oo)~~

~~(pp) A five digit operation counter.~~

~~(qq)~~

~~(rr) Electrically interlocked reversing contactors (preferably also mechanically interlocked).~~

~~(ss)~~

~~(tt) 240V, 50 Hz. AC space heater with switch and HRC fuses.~~

~~(uu)~~

~~(vv) Interior lighting fixture with lamp door switch and HRC fuses.~~

~~(ww)~~

~~(xx) Gasketted and hinged door with locking arrangement.~~

~~(yy)~~

~~(zz) Terminal blocks, internal wiring, earthing terminals and cable glands for power and control cables.~~

~~(aaa)~~

~~(bbb) Necessary relays, contactors, current transformers etc.~~

~~(ccc)~~

~~(ddd) Control Requirements for OLTC~~

~~(eee)~~

~~(fff) The following electrical control features shall be provided :~~

~~(ggg)~~

~~(hhh) Positive completion of load current transfer, once a tap change has been initiated, without stopping on any intermediate position, even in case of failure of external power supply.~~

~~(iii)~~

~~(jjj) Only one tap change from each tap change impulse even if the control switches or push button is maintained in the operated position.~~

~~(kkk)~~

~~(lll) Cut off of electrical control when manual control is resorted to. Cut off of a counter impulse for a reverse tap change until the mechanism comes to rest and resets the circuits for a fresh operation.~~

~~(mmm)~~

~~(nnn) Cut off of electrical control when it tends to operate the tap beyond its extreme position.~~

~~(ooo)~~

~~(ppp) Automatic Control of OLTC~~

~~(qqq)~~

~~(rrr) Automatic OLTC control shall include the following items :~~

~~(sss)~~

~~(ttt) Voltage setting device~~

~~(uuu)~~

~~(vvv) Voltage sensing and voltage regulating devices.~~

~~(www)~~

~~(xxx) Line drop compensator with adjustable R and X elements.~~

~~(yyy)~~

~~(zzz) Timer 5-25 seconds for delaying the operation of the tap changer in the first step for every tap change operation.~~

~~(aaaa)~~

~~(bbbb) Adjustable dead band for voltage variation~~

~~(cccc)~~

~~(dddd) OLTC Panel :~~

~~(eeee)~~

~~(ffff) The OLTC remote control equipment shall be suitable for 110V DC supply and shall be housed in an indoor sheet steel cubicle to be located in a remote control room. The OLTC control panel shall comprise of rigid welded structural frames made of structural steel section or of pressed and formed cold rolled steel and frame enclosures, doors and partitions shall be of cold rolled steel of thickness 2 mm. Stiffeners shall be provided wherever necessary. All doors, removable covers and plate shall be gasketed all around with neoprene gaskets. Panel shall be dust, weather and vermin proof providing degree of protection of IP54, colour of finish shade for interior and exterior shall be glassy white and light grey semi glossy shade 631 of IS-5 respectively. Earthing bus shall be of 25 x 6 mm copper.~~

~~(gggg)~~

~~(hhhh) (i) Control switch : Raise/Off/Lower~~

~~(iiii) (spring return to normal type)~~

~~(jjjj)~~

~~(kkkk) Auto/manual selector switch (maintained contact type)~~

~~(llll)~~

~~(mmmm) Tap position indicator~~

~~(nnnn)~~

~~(oooo) Facia type alarm annunciators with "accept" and "lamp test" facilities.~~

~~(pppp)~~

~~(qqqq) A.C. supply failure~~

~~(rrrr) Drive motor auto tripped~~

~~(ssss) Tap change delayed~~

~~(tttt)~~

~~(uuuu) Necessary auxiliary relays~~

~~(vvvv)~~

~~(wwww) Lamp indications for :~~

~~(xxxx) Tap change in progress~~

~~(yyyy) Lower limit reached~~

~~(zzzz) Upper limit reached~~

~~(aaaaa)~~

~~(bbbbb) Cable glands for power and control cables~~

~~(ccccc)~~

~~(ddddd) 240 V rated panel space heater with ON-OFF switch~~

~~(eeeee)~~

~~(fffff) Fluorescent type interior lighting fixture with lamp and door switch~~

~~(ggggg)~~

~~(hhhhh) HRC fuses~~

~~(iiiii)~~

~~(jjjjj) Terminal blocks~~

~~(kkkkk)~~

~~(lllll) Internal wiring~~

~~(mmmmm)~~

~~(nnnnn) Earthing terminal~~

~~(ooooo)~~

~~(ppppp) 6.4.8.2 Off Load Tap Changing Mechanism for Transformer~~

~~(qqqqq)~~

~~(rrrrr) Off circuit tap changing mechanism shall comprise the following~~

~~(sssss)~~

~~(ttttt) Operating handle of wheel, accessible from ground level~~

~~(uuuuu)~~

~~(vvvvv) Tap position indicator~~

~~(wwwww)~~

~~(xxxxx) Pad locking arrangement~~

~~(yyyyy)~~

~~(zzzzz) The tap-changer connections and contacts shall be accessible through an access hole having a bolted gasketted cover~~

~~(aaaaaa)~~

~~(bbbbbb) Fittings and Accessories~~

~~(cccccc)~~

~~(dddddd) The following fittings and accessories shall be provided with transformer~~

~~(eeeeee)~~

~~(ffffff) Name plate, rating plate and diagram plate.~~

~~(ggggggg)~~

~~(hhhhhh) Two earthing terminals on opposite ends of the transformer tank.~~

~~(iiiiii)~~

~~(jjjjjj) Inspection manhole in the cover.~~

~~(kkkkkk)~~

~~(llllll) Lifting lugs for the transformer, core assembly and tank core.~~

~~(mmmmmm)~~

~~(nnnnnn) Conservator, complete with filling plug, sump and drain valve, and a shut-off valve on the pipe connection between transformer tank and conservator, to permit removal of the conservator. The conservator shall be designed to maintain an oil seal through a temperature range of 100 Deg C.~~

~~(oooooo)~~

(ppppppp) Oil level indicator with minimum marking.

(qqqqqqq)

(rrrrrrr) Weather proof dehydrating breather with activated alumina or silicagel as the dehydrating agent.

(ssssss)

(ttttttt) Plain Oil level Gauge for all transformers up to 1.6 MVA. Above 1.6 MVA, Magnetic type oil level gauge with low oil level alarm contact, mounted on the conservators with waterproof and dustproof terminal box.

(uuuuuuu)

(vvvvvvv) Gas detector relays with separate alarm and trip contacts complete with shut-off valves.

(wwwwwww)

(xxxxxxx) Separate drain valve, oil sampling valve with plug and top filter valve shall be provided on the tank.

(yyyyyyy)

(zzzzzzz) Explosion vent with diaphragm for relieving pressure inside the transformer. The device shall be rain proof after operation. For transformers of 500 KVA and above an equaliser pipe connecting the pressure relief device to the conservator shall be supplied.

(aaaaaaaa)

(bbbbbbbb) Separately mounted, water proof and dustproof marshalling box housing the oil temperature indicator and winding temperature indicator with alarm and trip contacts and marshalling facilities for electrical devices mounted on transformer.

(ccccccc)

(ddddddd) For transformers rated 500 KVA and above. Adequate number of air vents for relieving trapped air during oil filling and during maintenance.

(eeeeeee)

(fffffff) Thermometer pockets and sensing element mounted on the transformer tank cover for measuring top oil temperature.

(ggggggg)

(hhhhhhh) Four jacking pads for lifting the transformer with jacks.

(iiiiiii)

(jjjjjjj) Pulling eyes and skids for the movement of the transformer.

(kkkkkkk)

(lllllll) Bidirectional wheels for movement of the transformers.

(mmmmmmm)

(nnnnnnn) Accessories for clamping the wheel mounted transformer to the foundation in order to withstand earthquake forces with a seismic acceleration of 0.2g.

(ooooooo)

(ppppppp) Transformer shall be supplied complete with insulating oil required for first filling plus 10% excess oil in non returnable drums.

(qqqqqqq)

(rrrrrrr)

(sssssss) Cable Terminations

(ttttttt)

(uuuuuuu) Cable termination boxes for transformers shall be suitable for dry termination of HV and LV cables. Non-magnetic gland plates shall be provided for the termination of single core cables.

(vvvvvvv)

(wwwwwwww) It shall be possible to remove the cable boxes without dismantling the cable glanding or draining the oil.

(xxxxxxx)

(yyyyyyy) Disconnecting links shall be provided to facilitate testing of the cable.

(zzzzzzz)

(aaaaaaaa) Tolerance on Losses

(bbbbbbbb)

(cccccccc) The permissible tolerances on the guaranteed values of transformer losses shall be as per IS 2026. The values of load- losses and No-load losses shall be within the values given in latest edition of CBIP manual for transformers.

(ddddddddd) Cost loading shall be done for capitalisation of losses at time of bid evaluation for all transformers as per CBIP Manual on transformers.

(eeeeeeee)

(fffffff) Rejection

(ggggggggg)

(hhhhhhhh) The Employer or Employer's Representative reserves the right to reject the transformer if the same does not meet the specification requirement, subject to tolerances as per IS 2026. The rejected transformers shall be replaced by transformers complying with the requirements of this specification at the Contractor's cost.

(iiiiiiii)

(jjjjjjjj) If the commissioning of the project is likely to be delayed by the rejection of a transformer, the Employer's Representative reserves the right to accept the rejected transformer until the replacement transformer is made available. Transporting the rejected and replacement transformers as well as installation and commissioning of both the transformers shall be at the Contractor's cost.

(kkkkkkkkk)

(lllllll) Drawings and Data

(mmmmmmmmm)

(nnnnnnnn) All Drawings, data, technical particulars ,calculations, detailed literature, catalogues , test certificates etc shall be submitted along with the bid/ after award of contract as specified under " Bid/Contract Drawings" , Part 3, General Requirements, Volume-2 of Bid Documents.

(oooooooo)

(ppppppppp)

(qqqqqqqqq)

(rrrrrrrr)

(ssssssss)

(ttttttttt)

(uuuuuuuuu)

11 11 kV Metal Enclosed Switchboards & Switchgears

13 Applicable Standards

15 The switchgear and its components shall conform to the latest applicable standards specified below :

Circuit Breakers	IS : 13118 / BS : 5311 / IEC : 60056,60694,IEC 62271-100
Metal Enclosed switchgear	IS : 3427 / BSEN:60298 / IEC:60298, IEC 62271-200
Current Transformers	IS : 2705 / BS : 7626
Voltage Transformers	IS : 3156 / BS : 7625 / IEC : 60186
Arrangement for Switchgear Busbars, Main Connections and Auxiliary wiring	IS : 5578, 11353
Busbar Support insulators	IS : 2544 / BS : 3297 / IEC :60273
Degree of Protection	IS : 13947 (Part 1) / IEC : 60947-1 / BSEN : 60529
Electrical Relays for Power system protection	IS : 3231, 3842 / BS : 142 / IEC : 60255
Electrical Indicating Instruments	IS : 1248 / BS : 89 / IEC :60051
High Voltage Fuses	IS : 9385 / BS : 2692 / IEC : 60282
AC Electricity Meters	IS : 722, 8530 / BS : 5685 / IEC : 60145,60211
Specification for copper rods and bars for electrical purposes	IS : 613

Code of practice for phosphating iron and steel	IS : 6005 / BS : 3189
Alternating current Switches for voltages above 1000 V	IS : 9920 / IEC : 60129,60265 & 60298
Low voltage fuses	IS : 13703 / BS 1362 / IEC 60269
Toggle switches	IS : 3452 / BS : 3676
Code of practice for selection, installation and maintenance of switchgear and control gear	IS : 10118
Control switches	IS:6875 / BSEN 60947 / IEC : 60947

16.1 Constructional Features

- Switchgear design shall be of metal enclosed, single front, free standing, floor mounted, fully compartmental execution having separate sections for each circuit. Each Circuit shall have a separate vertical panel with distinct compartments for main bus bars, circuit breaker, cable termination and auxiliary devices . The adjacent panels shall be completely separated by steel sheets except in bus bar sheet compartments where insulated barriers shall be provided to segregate adjacent panels. Compartments with doors for access to operating mechanism shall be so arranged as not to expose high voltage circuits. Switchgear cubicle shall be provided with hinged door on the front with facility for locking door handle. Switchboard shall be dust and vermin-proof and shall have a degree of protection of enclosure of IP 4X and the relay and meter compartments shall have a degree of Protection not less than IP 52. All removable covers shall be gasketed all around with neoprene or superior gaskets.
- Instruments, relays and control devices shall be flush mounted on hinged door of the metering compartment located in the front portion of cubicle. The metering compartment shall be properly shielded to prevent mal-operation of electronic equipment such as numerical / static relays due to electro-magnetic fields.
- Each switchgear cubicle shall be fitted with a label on the front and rear of the cubicle. Each switchboard shall also be fitted with label indicating the

switchboard designation, rating and duty. Each relay, instrument, switch, fuse and other devices shall be provided with separate label.

Sheet steel used for fabrication of switchgear, cubicles/boards shall be cold rolled. All panels shall comprise rigid welded structural frames made of structural steel sections or of pressed and formed cold rolled sheet steel of thickness not less than 2.5 mm. The frames shall be enclosed by sheet steel of at least 2 mm thickness. Stiffeners shall be provided wherever necessary. All doors, removable covers, gland plates, etc. shall be of at least 2 mm thickness and shall be gasketed all round the perimeter. All doors shall be supported by strong hinges of the disappearing or internal type and braced in such a manner as to ensure freedom from sagging, bending and general distortion of panel or hinged parts. All floor mounted panels / boards shall be provided with a channel base frame. It shall be possible to extend the switchboard on both sides. Total height of the switchgear Panel shall not exceed 2600 mm. The height of switches, push buttons and other hand operated devices shall not exceed 1800 mm and shall not be less than 800 mm.

The fully draw-out modules shall have all the circuit components mounted on withdraw able type steel chassis. All power and control connections shall be of the draw out type. It shall be possible to withdraw the chassis mounted circuit components without disconnecting any connections. All draw-out contacts shall be of silver plated copper.

In case of circuit breaker compartments, suitable barriers shall be provided between breaker and all control, protective and indication circuit equipment including instrument transformers such that no live parts are accessible. External cable connections shall be through separate cable compartments for power and control cables. Safety shutters shall be provided to cover up the fixed high voltage contacts on busbars when the circuit breaker carriage is moved to' test' and 'isolated' positions.

One metal sheet shall be provided between two adjacent vertical sections running to the full height of the switchboard except for the horizontal busbar compartment. However, each shipping section shall have metal sheets at both ends. After isolation of the power and control connections of a circuit, it shall be possible to carry out maintenance in a compartment safely, with the bus bars and adjacent circuits alive

~~Circuit Breaker~~

~~Circuit breakers shall be vacuum type with three separate single pole interrupting units, operated through a common shaft by a sturdy operating mechanism. Surge Arrestors shall be provided for each motor / transformer feeder . Circuit Breakers shall be re strike free, stored energy operated and trip free type. Circuit breaker along with its operating mechanism shall be mounted on a wheeled carriage moving on guides, designed to align correctly and allow easy movement. Plugs and sockets for power circuits shall be silver faced and shall be insulated with suitable insulating material shrouds. All corresponding components of circuit breaker cubicles of same rating shall be interchangeable with one another. Anti pumping relay and trip coil suspension relay shall be provided.~~

~~There shall be 'Service', 'Test' 'Fully withdrawn' positions for the breakers. In the 'Test' position the circuit breaker shall be capable of being tested for operation without energizing the power circuits, i.e. the control circuits shall remain undisturbed while the power contacts shall remain disconnected. Separate limit switches, each having a minimum of 2 'NO' + 2 'NC' contacts, shall be provided for both 'Service' and 'Test' positions of the circuit breakers.~~

~~Electrical tripping shall be performed by shunt trip coils. "Local / Remote" selector switch lockable in "Local" position shall be provided on the cubicle door. 'Red' and 'Green' indicating lamps shall be provided on cubicle door to indicate breaker close and open positions. Breaker "Service" and "Test" positions shall be indicated by separate indicating lamps on the cubicle door, in case mechanical indication of "Service" and "Test" positions are not available on the cubicle door.~~

~~Connection of the control / interlocking circuits between the fixed portion of the cubicle and the breaker carriage shall be preferably by means of plug socket arrangement.~~

~~Operating Mechanism Control~~

~~Circuit breakers shall be operated by a motor spring charging type of mechanism. The mechanism shall be complete with motor, opening spring, closing spring and all accessories to make the mechanism a complete operating unit.~~

~~Operating mechanism shall normally be operated from the breaker cubicle itself.~~

~~The tripping spring shall be charged by the closing action, to enable quick tripping. Closing of the circuit breaker shall automatically initiate recharging of the springs to enable the mechanism to be ready for the next closing stroke. Charging time for the springs shall not exceed 30 seconds. It shall be possible to manually charge the springs in an emergency. Transfer from motor to manual charging shall automatically disconnect the charging motor. All operating mechanisms shall be provided with "ON" - "OFF" mechanical indication. The charging mechanism shall be provided with mechanical indicators to show "charged" and "discharged" conditions of the spring. Failure of any spring, vibration or mechanical shock shall not cause tripping or closing of the circuit breaker.~~

~~Only one closing operation of the circuit breaker shall result from each closing impulse (manual or electrical), even if the breaker trips while the control device (manual or electrical) is being held in the "close" position.~~

~~The circuit breaker mechanism shall make one complete closing operation, once the push button (PB) or control switch has been operated and the first device in the control scheme has responded, even though the PB or control switch is released before the closing operation is complete, subject to the condition that there is no counter- impulse for tripping.~~

~~Means shall be provided to manually open and close the breakers slowly, when the operating power is not available, for maintenance and adjustments. A local manual trip device shall also be provided on the operating mechanism.~~

~~Circuit breaker control shall be on 110 V DC. Closing coils and other auxiliary devices shall operate satisfactorily at all voltages between 80-110 % of the control voltage. Trip coils shall operate satisfactorily between 50 -110 % the rated control voltage.~~

~~Safety Interlocks And Features~~

~~Withdrawal or engagement of a circuit breaker shall not be possible unless it is in the open position.~~

~~Operation of a circuit breaker shall not be possible unless it is in service position, withdrawn to test position or fully drawn out. It shall not be possible to close the circuit breaker electrically in the service position, without completing the auxiliary circuit between the fixed and moving portions.~~

Circuit breaker cubicles shall be provided with safety shutters operated automatically by the movement of the circuit breaker carriage to cover the stationary isolated contacts when the breaker is withdrawn. Padlocking facilities shall be provided for locking the shutters positively in the closed position. It shall, however, be possible to open the shutters intentionally against spring pressure for testing purposes.

The circuit breaker carriage shall be earthed before the breaker reaches the test position from fully withdrawn position. In case of breakers with automatic disconnecting type of auxiliary disconnects, the carriage shall be earthed before the auxiliary disconnects are made and the carriage earthing shall break only after the auxiliary disconnects break.

Caution nameplate, "Caution Live Terminals" shall be provided at all points where the terminals are likely to remain live and isolation is possible only at remote end, i.e. incomer to the switchboard. Suitable interlock shall be wired for the purpose.

Earthing

- Copper earthing bus shall be provided and extended throughout the length of the switchboard. It shall be bolted to the framework of each unit and brazed to each breaker earthing contact bar. It shall be located at the bottom of the board. The earth bus shall have sufficient cross section to carry the momentary short circuit and short time fault current for at least 1 second or higher without exceeding maximum allowable temperature rise. The earth bus shall be properly supported to withstand stresses induced by the momentary short circuit current.
- Suitable clamp type terminals at each end of the earth bus shall be provided to suit the size of the earthing conductors. Bolted joints, slices, tap, etc. to the earth bus shall be made with at least two bolts. Positive earthing of circuit breaker frame shall be maintained when it is in the connected position and in all other positions whilst the auxiliary circuits are not totally disconnected.
- Hinged doors shall be earthed through flexible earthing braid of adequate cross section. All non-current carrying metal work of the switchboard shall be effectively bonded to the earth bus.
- Positive connection of the frames of all the equipment mounted in the switchboard to the earth busbar shall be maintained through insulated conductors of size equal to the earth busbar or the load current carrying conductor, whichever is smaller.

- All instrument and relay cases shall be connected to earth busbar by means of 1100V grade, green coloured, PVC insulated, stranded, tinned copper, 2.5 sq. mm conductor looped through each of the earth terminals.

Circuit / Busbar Earthing Facility

- It shall be possible to connect each circuit or set of 3 phase bus bars of the switchboard to earth through earthing switches. Earthing switches / earthing devices shall be mechanically interlocked with the associated breakers to prevent accidental earthing of live circuit or bus bars. In case the earthing facility comprises earthing trucks to be inserted in place of circuit breakers, separate earthing trucks shall be supplied for each type / size of breaker. The earthing facilities proposed to be provided by the Bidder shall be clearly detailed in the Bid and shall be subject to Employer's approval. Auxiliary contacts (min. 2 NO + 2 NC) shall be provided on each earth switch / earthing device and shall be wired to the terminal block for interlocking purpose.

Annunciators

- Annunciator shall be of facia type with translucent plastic window for each alarm point. Annunciator facia plates shall be engraved in block lettering with respective alarm inscriptions. The inscriptions shall be clearly readable and visible when the respective facia light is lighted. Each annunciation window shall be provided with two lamps to provide redundancy against lamp failure. Lamps shall be replaceable from the front. Lamps shall be of clustered LED type.
- All facia annunciator points shall be suitable to accept external contacts of either 'NO' or 'NC' self or hand reset type for initiating the annunciation sequence. Annunciators shall be suitable for accepting fleeting faults of duration as less as 15 milliseconds.
- For static annunciator schemes, special precaution shall be taken by the Contractor to ensure that spurious alarm conditions do not appear due to influence of external magnetic fields on the annunciator wiring and switching disturbances from the neighbouring circuits within the panels / desks.
- A "Lamp Test" push button shall be provided for each individual panel's group of annunciators to limit the sudden drain on the battery. Provision of testing facilities for flasher and audible alarm circuits of annunciators is desirable. The Contractor shall give the details of the offered scheme.

~~Annunciator shall have following features:~~

~~Suitable for annunciating subsequent faults immediately after the sound cancel of the previous fault.~~

~~During lamp test, if a fault occurs, the corresponding lamp circuit shall be automatically disconnected from the "lamp test" circuit and shall start flashing.~~

~~Designed to prevent mal-operation of the scheme or sequence when the push buttons are pressed incorrectly or in the wrong order.~~

~~"Alarm Supply Failure" Alarm scheme similar to the normal annunciation sequence, but shall operate on a different DC supply or on AC auxiliary supply~~

~~Indicating Instruments & Meters~~

~~Electrical indicating instruments shall be 144mm x 144mm square with 240º scale. Taut band type of instruments is preferred. Taut band moving coil instruments for use on AC systems shall incorporate built-in transducers.~~

~~Instrument dials shall be white with black numbers and lettering. A red line shall be drawn on each scale to represent rated conditions.~~

~~Normal maximum meter reading shall be of the order of 60 % normal full scale deflection. Ammeters for motor feeders shall have suppressed scale to show current from full load up to six times the full load current.~~

~~Instruments shall have accuracy class of 1.0 or better. The design of the scales shall be such that it can read to a resolution corresponding to 50% of the accuracy class index.~~

~~Ammeters and current coils of Watt meters and Voltmeters shall continuously withstand 120% of rated current and 10 times the rated current for 0.5 sec., without loss of accuracy. Voltmeters and potential coils of Watt meters and Varmeters shall withstand 120% of rated voltage continuously and twice the rated voltage for 0.5 sec. without loss of accuracy.~~

~~Alternatively, instruments can be electronic / digital type with LCD display. These instruments should have high performance ratio and can be equipped with digital output (for alarms) or with interfacing facilities for communication and remote reading of parameters.~~

~~Metering Instruments~~

- ~~Watt-hour meters shall be of the induction type and shall be provided with reverse running stops.~~
- ~~Watt-hour and Varhour meters shall be of the three phase two element type of accuracy class 1.0, suitable for measurement of unbalanced loads in three phase three wire circuits.~~
- ~~Watt-hour and Varhour meters shall be suitable for operation from the secondary of CTs and VTs. They shall be provided with a separate 3 phase 4 wire type test blocks for the testing of the meters without disturbing the CT and VT secondary connections.~~
- ~~Alternatively, instruments can be electronic / digital type with LCD display. These instruments should have high performance ratio and can be equipped with digital output (for alarms).~~
- ~~—~~
- ~~Control and Selector Switches~~
- ~~—~~
- ~~Control and instrument switches shall be heavy duty rotary type, provided with escutcheon plates clearly marked to show operating position and suitable for semi-flush mounting with only the switch front plate and operating handle projecting out. The connections shall be from the back. The contact assembly at the back of the switch shall be enclosed in dust tight removable covers.~~
- ~~The control switches shall be 3 position, spring return to neutral type. They shall be provided with contacts to close in 'normal after close' and 'normal after trip' position. Each switch shall have external red and green indicating lamps, (except when discrepancy type switches are called for). In addition, a semaphore indicator shall be provided for earthing switch.~~
- ~~Contacts of the switches shall be spring assisted and contact faces shall be of silver / silver alloy. Springs shall not be used as current carrying parts. Contact rating and configurations of the switches shall be adequate for the functions desired.~~
- ~~Instrument selector switches shall be of the maintained (stay-put) type. Ammeter and voltmeter selector switches shall have four stay put positions. Ammeter selector switches shall have make-before-break type contacts so as to prevent open circuiting of CT secondary when changing the position of the switch.~~
- ~~Lockable type switches, which can be locked in a particular position, shall be provided, if required.~~
- ~~Emergency stop buttons, if any, shall incorporate 'stay-put' features with independent reset facilities.~~
- ~~—~~

- ~~Indicating Lamps / Pilot Lamps~~
- ~~~~
- ~~Indicating lamp shall be of the double contact, bayonet cap type rated for operation at either 230 V AC or at the specified DC system voltage as applicable. Lamps shall be provided with translucent lamp covers.~~
- ~~Clustered LED type lamps shall be provided. Lenses shall be glass or plastic in standard colours, red, green, blue, white and amber, in accordance with IEC 60073. Bulbs and lenses shall be interchangeable and easily replaceable from the front of the panel. Tools, if any, which are required for replacing the bulbs and lenses, shall also be included in the scope of supply.~~
- ~~Miniature pilot lamps may be provided with plastic marking plate contained inside square (or rectangular) front lens to provide indication of legend or symbols engraved on the marking plate.~~
- ~~~~
- ~~The basis of colours shall be as follows:~~
- ~~Red : Flow of energy.~~
- ~~Green : No flow of energy.~~
- ~~White : Supervision of power available, relay coil healthy, etc.~~
- ~~Amber : Disagreement with original condition, 'abnormal' condition or~~
- ~~'sequence on' condition.~~
- ~~~~
- ~~Push Buttons~~
- ~~~~
- ~~Push buttons shall be of momentary contact type with rear terminal connections. The colour of the push button actuator shall be red for 'OPEN / STOP' and green for 'CLOSE / START'. The push button knob shall be suitably shrouded to prevent inadvertent operation. The push buttons shall be provided with integral inscription plates engraved with their designation.~~
- ~~All push buttons shall have independent, potential free, 2NO + 2NC contacts. The contact faces shall be of silver / silver alloy. The contacts shall be rated 10A and capable of breaking inductive load of 5A at 110V DC.~~
- ~~~~
- ~~Space Heaters~~
- ~~~~
- ~~Adequately rated anti-condensation space heaters shall be provided for each switchboard / cubicle. Space heater shall be of the industrial strip continuous duty type, rated for operation on a 240 V, 1 phase, 50 Hz, AC~~

system. Space heater shall be provided with a single pole MCB with overload and short circuit release, a neutral link and a thermostat to cut off the heaters at 35 degree

- Cubicle Lighting / Receptacle

- Each cubicle shall be provided with interior lighting by means of 18 W fluorescent tube lighting fixture. An MCB shall be provided for the lighting circuit. The lighting fixture shall be suitable for operation from a 240 V, 1 ph, 50 Hz, AC supply. A 240 V, 1 phase, AC receptacle (socket) plug point shall be provided in the interior of each panel with an MCB.

- Power and Control Cable Termination

- Terminals for power connections shall be complete with adequate phase segregating insulating barriers, shrouds and suitable crimping type of lugs for terminating the cables.
- Double compression type glands with armour and bonding clamps for the termination of all solid dielectric multicore cables shall be provided. They shall be designed to secure the armour wires to provide electrical continuity between the armour and the threaded fixing component of the gland and to provide watertight seals between the cable outer sheath and gland and between the inner sheath and threaded fixing component. The gland shall preferably project above the gland plate to avoid entry of moisture.
- Earthing connectors between cable armour and earth shall be routed outside the cable gland in an approved manner. Gland insulation shall be capable of withstanding test for appropriate high voltage for one minute.
- Cable terminations for HV / MV cables shall be heat / cold shrinkable type. Adequately sized shrouds / bolts shall be provided at connections to completely cover the terminations.
- Where core balance type current transformers are provided on the feeder cables for earth fault protection, glands for cables shall be insulated from earth in an approved manner.

- Wiring For Control and Protective Circuits

- All low voltage wiring for control, protection and indication circuits shall be carried out with 1100 V grade, PVC insulated cable with stranded,

tinned copper conductor of minimum 1.5 sq. mm size. The size of conductor for CT circuits shall be minimum 2.5 sq. mm.

- All wiring shall be run on the sides of panels and shall be neatly bunched and cleated without affecting access to equipment mounted in the panel. The wiring shall be bound and supported by clamping, roughing or lacing. Spiral wrapping will not be accepted. Wireways shall not be more than 50% full. Adequate slack wire shall be provided to allow for one restripping and reconnection at the end of each wire. When screened cables or wires are necessary, an insulating sheath shall be included. Wiring and supports shall be of fire resistant material.
- Wiring shall only be jointed or teed at terminals. Terminals of the clamp type shall not have more than two wires connected.
-
- Termination and Ferrules
-
- Engraved core identification ferrules, marked to correspond with the wiring diagram, shall be fitted to each wire and each core of multicore cables terminated on the panels.
- Moisture and oil resisting insulating material shall be used. The ferrules shall be of the interlocking type and shall grip the insulation firmly without falling off when the wire is removed.
- All wires forming part of a tripping circuit shall be distinctively marked. Spare auxiliary contacts of electrical equipment shall be wired to terminal blocks.
-
- Control Wiring Terminal Blocks
-
- Terminal blocks shall be of 1000 V grade and stud type. Brass stud of at least 6 mm dia. with fine threads shall be used and securely locked within the mounting base to prevent turning. Each terminal shall comprise two threaded studs, with a link between them, washers, and matching nuts and locknuts for each stud. Connections to the terminals shall be at the front.
- Terminals shall be numbered for identification, grouped according to function. Engraved 'black on-white' labels shall be provided on the terminal blocks describing the function of the circuit.
- Terminals for circuits with voltage exceeding 110 V shall be shrouded. Terminal blocks at different voltages shall be segregated into groups and distinctively labelled. Terminals used for connecting current transformer secondary leads shall be 'disconnecting and shorting' type with a facility for earthing the secondary.

- ~~Terminal blocks shall be arranged with 100 mm clearance, between any two sets. Separate terminal stems shall be provided for internal and external wiring respectively. All wiring shall be terminated on terminal blocks, using crimping type lugs or claw type of terminations.~~
- ~~BusBars~~
- ~~The Bus bars shall be of electrical grade, high conductivity, copper and shall be provided with minimum clearances as per relevant IS. Bus bar cross section shall be uniform throughout the length of the switchgear.All bus bars and bus taps shall be insulated with close fitting sleeve of hard, smooth, dust and dirt free, heat shrunk PVC insulation of high dielectric strength, to provide a permanent non-ageing and non-tracking protection, impervious to water, tropical conditions and fungi. The insulation shall be non inflammable and self extinguishing type and in fast colours to indicate phases. The dielectric strength and properties shall hold good for the temperature range of 0 to 95 degree centigrade. If the insulating sleeve is not coloured, bus bars shall be colour coded with coloured PVC tape at suitable intervals.~~
- ~~Busbar joints shall be of the bolted type. Spring washers shall be provided to ensure good contact at the joints. Busbars shall be thoroughly cleaned at the joints and suitable contact grease shall be applied just before making a joint.~~
- ~~Direct access to, or accidental contact with busbars and primary connections shall not be possible. All apertures and slots shall be protected by baffles to prevent accidental shorting of busbars due to insertion of maintenance tools.~~
- ~~Sequence of red, yellow and blue phases and neutral for four-pole equipment shall be left to right and top to bottom, for horizontal and vertical layouts respectively.~~
- ~~Current & Voltage Transformers~~
- ~~Current transformers shall be of cast resin, bar primary type unless specified otherwise , suitable for continuous operation at the ambient temperature prevailing inside the switchgear enclosure and shall have polarity markings indelibly marked on each transformer and at the lead terminations at the associated terminal block. The class of insulation shall be Class E or better. Current transformers shall be able to withstand the thermal and mechanical stresses resulting from the maximum short circuit and momentary duties of the switchgear. For wound primary type CTs, the~~

short time current rating shall not be less than 0.5 sec. CT core laminations shall be of high grade silicon steel.Where multi-ratio current transformers are specified, a label shall be provided, clearly indicating the connections required for the alternative ratios. These connections shall also be shown on panel wiring diagrams. Identification labels shall be fitted giving type, ratio, rating, output and serial numbers and duplicate rating labels are to be fitted on the exterior of the mounting chambers suitably located to enable reading without the removal of any cover or metal sheeting forming part of the structure of the switchboard.

- Magnetization characteristics, calculated performance and protective settings shall be provided by the Contractor. All Voltage Transformers shall be of Single Phase type. The bus VT's shall be housed in a separate panel in a truck so as to be fully with draw able . All Voltage transformers shall have HRC fuses on Primary and Secondary Side. There
- Shall be provision for changeover on secondary side of Voltage Transformers to have alternate arrangement in case one Voltage Transformer fails.
-
-
- Relays
-
- All Protective relays shall be numerical type . Numerical relays shall have appropriate setting ranges , accuracy, resetting ratio and other characteristics to provide required sensitivity.
-
- All protective relays shall be flush mounted at the front with connections at the rear in draw out cases with built in test facilities, including test plugs. All auxiliary relays and timers shall be supplied in non-drawout cases.
-
- All numerical relays shall have keypad to allow relay settings from relay front. Resetting knobs shall be accessible from the front on removing the external cover and shall be external to the case.
-
- All numerical relays and timers shall be rated for control supply voltage specified
- and be capable of satisfactory continuous operation between 70 % to 110 % of the rated voltage. Making, Carrying and Breaking Current ratings of the relay Contacts
- shall be adequate for the circuits in which they are used.
-

- ~~The numerical relays shall have communication, Metering and Monitoring Facility.~~
- ~~The communication facility shall have two Ports , local front port for laptop communication and the second port , an IEC 61850 port, for LAN Communication with LAN.~~
-
- ~~The numerical processor shall be capable of measuring and sharing values of a wide range of quantities ,events ,faults and disturbance recordings with time stamping using internal real time clock. Battery back up for real time clock in the event of power failure shall be provided.~~
-
- ~~Numerical Relays shall have diagnostic feature with self check for power failure, Programmable routines, memory and main CPU Failures etc.~~
-
- ~~The Protective relays shall have adequate number of potential free contacts (Programmable) . The Contacts shall be suitable for directly wiring in the breaker closing and tripping circuits operating from 110 V DC Control Voltage.~~
-
- ~~The current operated relays shall have provision for 4 Sets of CT Inputs and Voltage operated relays shall have provision for 3 PT inputs. Relays shall be suitable for CT secondary current suitable for CT Secondary current of 1 A / 5 A selectable at Site.~~
-
- ~~Numerical Relays shall be immune to any kind of electromagnetic interference and capacitance effect due to length of connected control cables.~~
-
- ~~Timer function shall be programmable for ON/OFF delays.~~
-
- ~~Numerical Relays shall be able to provide supervisory function such as trip circuit monitoring , circuit breaker monitoring , PT & CT supervisions and recording facilities with post fault analysis.~~
-
- ~~All relays shall withstand minimum test voltage of 2 KV AC RMS for one minute.~~
-
- ~~Numerical relays shall have two level password protections , one for read only and other for authorization for modifying the setting etc.~~
-

- ~~Energy monitoring and Management~~
- ~~Necessary Provisions & features shall be incorporated to enable energy monitoring~~
- ~~/energy management for the installation.~~
- ~~I / O & Other Data for Instrumentation, Control & Automation System~~

~~Necessary provisions shall be incorporated to meet the requirements indicated in~~

~~(a) I / O Schedules~~

~~(b) Data Transfer Schedule~~

~~(c) Alarm Schedule of Particular requirement of Instrumentation, Control & Automation System,Part 13, Volume -2 of the Bid document .~~
~~(d)~~
~~(e) Drawings and Data~~
~~(f)~~
~~(g) All Drawings, data, technical particulars ,calculations, detailed literature, catalogues ,~~
~~(h) test certificates etc shall be submitted along with the bid/ after award of contract as~~
~~(i) specified under " Bid/Contract Drawings" , Part 3, General Requirements,~~
~~(j) Volume-2 of Bid Documents .~~
~~(k)~~

2.4 415 V Metal Enclosed Switchgears (PCC) / MCC

2.4.1 Applicable Standards

The switchgear and components shall conform to the latest applicable standards specified below. .

Switchgear General Requirements	IS:13947/BS:5486/IEC:60947
Factory Built Assemblies of SWGR and Controlgear for Voltages upto and including 1000V AC & 1200V DC	IS:8623/BS:5486/IEC:60439
Air Break Switches	IS:13947-P3 /BSEN60947

	/IEC:60947-3
Moulded Case Circuit Breaker	IS 2516 / IEC 60947-2/ BS EN 60947-2
Miniature Circuit Breakers	IS:8828/BSEN:60898
Low voltage Fuses	IS:13703/BS:1362/IEC:60269-1
Contactors	IS:13947/BS EN60947-4 /IEC:60947-1
Starters	IS:13947/BS EN60947-4/ IEC:60292-1TO 4
Control Switches / Push buttons	IS:6875 / BSEN 60947
Current Transformers	IS:2705/BS:7626
Voltage Transformers	IS:3156/BS:7625/IEC:60044, 60186
Indicating instruments	IS:1248/BS:89/IEC:60051
Marking and Identification of Conductors and Apparatus Terminals	IS:11353/BS:159
A.C. Electricity Meters	IS:722, 8530/BS:5685 / IEC 60145,60 211
Degree of Protection	IS:13947/IEC:60947-P1
Selection installation and maintenance of switchgear and control gear	IS:10118
Code of practice for phosphating iron and steel	IS:6005/BS:3189
Specification for copper rods and bars for electrical purposes	IS:613
Control transformers for switchgear and controlgear voltage not exceeding 1000V AC	IS:12021

2.4.2

Features of Construction

(a) The switchgear shall be metal enclosed, dust proof, modular type, suitable for indoor floor mounting and shall have following features.

(i) Total height of switchgear shall not exceed 2300 mm. Height of Switches, Push buttons shall not exceed 1800 mm and shall not be less than 700 mm.

(ii) Shall be double front execution and fixed type

(iii) Shall have designation labels both on front and rear sides

(iv) Shall be provided with proper gasketing for removable covers, doors, between panels and base frame and all around the perimeter of adjacent panels.

(v) Degree of Protection shall be IP54 for indoor & IP55 for Outdoor.

(vi) Thickness of CRCA Sheet is 2mm.

~~(b)~~ Switchgear shall be divided into distinct vertical sections each comprising :

(i) A completely enclosed busbar compartment running horizontally

(ii) Enclosed vertical busbars serving all modules in vertical section

(iii) A separate horizontal enclosure for all auxiliary power and control buses

~~(iv)~~ if required.

(v) Vertical cable alley of 250mm wide covering entire height

(c) Operating devices shall be incorporated only in the front of switchgear

(d) Each shipping section shall have metal sheets at both ends

(e) Cable alley shall be provided with suitable hinged doors

(f) GS Earth bus of size 50mm x 10 mm shall be provided at the bottom.

(g) Rear of Single Front Switchgear shall be provided with removable panels with screws.

(h) All doors shall be with concealed type hinges and captive screws

(i) Each vertical section shall be equipped with 240 V , 1 Phase, 50 Hz space heater controlled by thermostat

(j) A 240 V, 1 phase, AC plug point shall be provided in the interior of each cubicle with on-off switch for correction of head lamps

(k) Interchangeability

All identical equipment and corresponding parts be fully interchangeable without any modifications.

(l) Main and Auxiliary Buses

(i) Switchgear busbars shall be of uniform cross section throughout the length and made of high conductivity, electrical grade hard drawn copper conductor.

(ii) Busbar shall be fully insulated by encapsulation in epoxy resin with moulded caps protecting all joints and shall be adequately supported to withstand stresses developed due to short circuits. Supports shall be of glass reinforced phenolic material or cast resin.

(iii) Busbar joints shall be provided with contact grease at the joints and shall be complete with tensile steel bolts and belleville washers and nuts.

2.4.3 Air Circuit Breaker (ACB)

(i) Circuit breakers shall be operated by a motor spring charging type of mechanism. The motor operated spring charged mechanism shall be complete with motor, opening spring, closing spring and all accessories to make the mechanism a complete operating unit.

(ii) The tripping spring shall be charged by the closing action, to enable quick tripping. Closing of the circuit breaker shall automatically initiate recharging of the springs to enable the mechanism to be ready for the next closing stroke. Charging time for the springs shall not exceed 30 seconds. It shall be possible to manually charge the springs in an emergency. Transfer from motor to manual charging shall automatically disconnect the charging motor. The charging mechanism shall be provided with mechanical indicators to show "charged" and "discharged" conditions of the spring. Failure of any spring, vibration or mechanical shock shall not cause tripping or closing of the circuit breaker.

(iii) Only one closing operation of the circuit breaker shall result from each closing impulse (manual or electrical), even if the breaker trips while the control device (manual or electrical) is being held in the "close" position.

(iv) The circuit breaker mechanism shall make one complete closing operation, once the push button has been operated and the first device in the control scheme has responded, even though the PB is released before the closing operation is complete, subject to the condition that there is no counter-impulse for tripping.

(v) Means shall be provided to manually open and close the breakers slowly, when the operating power is not available, for maintenance and adjustments. A local manual trip device shall be provided on the operating mechanism.

(vi) All operating mechanisms shall be provided with "ON" - "OFF" mechanical indication.

(vii) Closing coils and other auxiliary devices shall operate satisfactorily at all voltages between 85-110 % of the control voltage. Trip coils shall operate satisfactorily between 70 -110 % the rated control voltage.

(viii) The Breaker shall be provided with Microprocessor based releases for Inverse-time delayed overload releases for the phases, Short-time delayed short-circuit releases and earth-fault releases.

(ix) The breaker service Short Circuit breaking capacity (I_{CS}) shall be equal to ultimate Short Circuit capacity (I_{CU}) and shall be equal to short time withstand current of Breaker (I_{CW}).

2.4.4 Moulded Case Circuit Breaker (MCCB)

——MCCBs shall be of the air break, quick make, quick break and trip free type and shall be totally enclosed in a heat resistant, moulded, insulating material housing. MCCBs shall have an ultimate short circuit capacity not less than the short circuit current Specified .MCCBs shall have a service short circuit breaking capacity (I_{CS}) equal to the ultimate short-circuit capacity (I_{CU}).

——Each pole of MCCB shall be fitted with a bi-metallic thermal element for inverse time delay protection and a magnetic element for short circuit protection. Alternatively, they shall be fitted with a solid state protection system. Such a protection system shall be fully self-contained, needing no separate power supply to operate the circuit breaker tripping mechanism. Thermal element shall be adjustable. Adjustments shall be made simultaneously on all poles from a common facility. Thermal elements shall be ambient temperature compensated.

The MCCBs shall be provided with the following features.

- Common trip bar for simultaneous tripping of all poles
- Shrouded terminals
- Time for clearing short circuit current of 20 msec.
- 2 NO + 2 NC auxiliary contacts

2.4.5 Switches and Fuses

(a) 415 V air-break switched shall be of the load break, fault make, group operated type. For use on 3-phase systems, the switches shall be of the triple pole type with a link for neutral wire. For use on single phase system and d-c systems, the switches shall be of the two pole type.

(b) Switches shall be of the heavy duty, quick make and quick break type. Switch contacts shall be silver plated, and contract springs shall be of stainless steel. Switch handles shall have provision for locking in both fully open and fully closed positions. Mechanical ON-OFF indication shall be provided on the switches.

(c) Switches for controlling motor circuits shall be of the load break, fault make type, and shall be capable of breaking locked rotor current of the associated motor.

(d) 415 V switches and fuses shall be provided with the following interlocks so that :

(e) The fuses are not accessible unless the switch is in fully open condition

(f) It is not possible to close the switch when the fuse cover is open, but an authorised person may override the interlock and operate the switch. After such an operation, the cover shall be prevented from closing if the switch is left in the 'ON' position.

(g) All fuses shall be of the HRC cartridge type, mounted on plug-in type of fuse bases. Fuses shall be provided with visible indicators to show that they have operated.

(h) Earthing and neutral lines in main supply circuits shall be of solid silver plated copper and be of the bolted pattern.

(i) Fuses and links functionally associated with the same circuit shall be mounted side by side.

2.4.6 Miniature Circuit Breaker (MCB)

MCB shall be hand operated, air break, quick make, quick break type.
Operating mechanisms shall be mechanically trip-free from the operating knob to prevent the contacts being held closed under overload or short-circuit conditions.
Each pole shall be fitted with a bi-metallic element for overload protection and a magnetic element for short-circuit protection. Multiple pole MCBs shall be mechanically linked such that tripping of one pole simultaneously trips all the other poles. The magnetic element tripping current classification shall be of the type suitable for the connected load. Where this is not specified, it shall be Type C. The short circuit rating shall be not less than that of the system to which they are connected.

2.4.7 –Contactors

The power contactors used in the switchboard shall be of, air break, single throw, triple pole, electromagnetic type. Contactors shall be suitable for uninterrupted duty and rated for Class AC3 duty in accordance with the latest edition of IS 13947.

Operating coils of all contactors shall be suitable for operation on 240 V, single phase, 50 Hz supply. Contactors shall be provided with at least two pairs of NO and NC auxiliary contacts. Contactors shall not drop out at voltages down to 70 % of coil rated voltage. Contactors shall be provided with a three element, positive acting, ambient temperature compensated, time lagged, hand reset type thermal overload relay with adjustable settings. The hand reset button shall be flush with the front door of the control module, and shall be suitable for resetting the overload relay with the module door closed. Relays shall be either direct connected or CT operated. Overload relay and reset button shall be independent of the "Start" and "Stop" push buttons. All contactor shall all be provided with single phasing preventer (SPP).

Motor starters shall be complete with auxiliary relays, timers and necessary indications.

2.4.8 –Current Transformers

(a) Current Transformers shall be Cast Resin type.

(b) Current transformers shall have polarity markings indelibly marked on each transformer and at the lead terminations at the associated terminal block.

(c) Current transformers shall be able to withstand the thermal and mechanical stresses resulting from the maximum short circuit and momentary duties of the switchgear, as indicated in the Technical Specification.

(d) CT core laminations shall be of high grade silicon steel.

(e) Identification labels shall be fitted giving type, ratio, rating, output and serial
numbers.

2.4.9 Voltage Transformers

(a) Voltage Transformers shall be Cast Resin type.

(b) Secondary and tertiary windings of voltage transformers shall be rated for a three phase line to line voltage of 110 V.

(c) It shall be possible to replace voltage transformer fuses easily without having to de energiser the main bus-bars.

2.4.10 -Indicating Instruments & Meters

Electrical indicating instruments shall be 110 mm square with 240º scale. Taut band type of instruments is preferred. Taut band moving coil instruments for use on AC systems shall incorporate built-in transducers. Instrument dials shall be white with black numbers and lettering .Normal maximum meter reading shall be of the order of 60 % normal full scale deflection. Ammeters for motor feeders shall have suppressed scale to show current from full load up to six times the full load current. Watt hour meters shall be of the induction type and shall be provided with reverse running stops. Instruments shall have an accuracy of Class 1.0.

2.4.11 Indicating Lamps

Indicating lamps shall be of the cluster LED type, with low watt consumption. Indicating lamp shall be of the double contact, bayonet cap type rated for operation at either 240 V AC or at the specified DC system voltage as applicable. Lamps shall be provided with translucent lamp covers. Bulbs and lenses shall be interchangeable and easily replaceable from the front.

2.4.12 Push Buttons

"Start" and "Stop" push buttons shall be coloured green and red respectively. Stop Push Button shall be lockable stay-put type with Mushroom head.

2.4.13 Space Heaters

Adequately rated anti-condensation space heaters shall be provided, one for each control panel, for each switchboard and for each marshalling kiosk.Space heater shall be of the industrial strip continuous duty type, rated for operation on a 240 V, 1 phase, 50 Hz, AC system.Each space heater shall be provided with a single pole MCB with overload and short circuit release, a neutral link and a control thermostat to cut off the heaters at 350 C.

2.4.14 Safety Arrangements

All terminals, connections and other components, which may be "live" when front access door is open, shall be adequately screened. It shall not be possible to obtain access to an adjacent cubicle or module when any door is opened. Components within the cubicles shall be labelled to facilitate testing.

2.4.15 Earthing of Switchboards / Panels

Each switchboard, control panel, etc. shall be provided with an earth busbar running along its entire length. The earth bus bar shall be located at the bottom of the board/panel.

Earth bus bars shall be of copper and shall be rated to carry the rated symmetrical short circuit current of the associated board/panel for one second, unless otherwise specified. Earth bus bars shall be properly supported to withstand stresses induced by the momentary short circuit current of value equal to the momentary short circuit rating of the associated switchboard/panel.

Positive connection of the frames of all the equipment mounted in the switchboard to the earth bus bar shall be maintained through insulated conductors of size equal to the earth bus bar or the load current carrying conductor, whichever is smaller.

All instrument and relay cases shall be connected to earth bus bar by means of 1100 V grade, green coloured, PVC insulated, stranded, tinned copper, 2.5 sq. mm conductor looped through the case earth terminals.

2.4.16 Internal Wiring

The internal wiring shall be carried out with 650/1100V grade, PVC insulated, stranded conductor wires. The minimum size of conductor for power circuits shall be 4 Sq.mm copper or equivalent size aluminium conductor. Control circuits shall be wired with copper conductor of atleast 1.5 Sq.mm.

~~**16.2 I / O & Other Data for Instrumentation, Control & Automation System**~~

~~**16.3**~~

~~**16.4 Necessary provisions shall be incorporated to meet the requirements indicated in**~~

~~**16.5**~~

~~**16.6 I / O Schedules**~~

~~**16.7**~~

~~**16.8 Data Transfer Schedule**~~

~~**16.9**~~

~~**16.10 Alarm Schedule of Particular requirement of Instrumentation, Control & Automation System, Part-13, Volume -2 of the Bid document .**~~

~~**16.11**~~

2.4.18 Drawing and Data

All Drawings, data, technical particulars, calculations, detailed literature, catalogues, test certificates etc shall be submitted along with the bid/ after award of contract. ~~as specified under " Bid/Contract Drawings" , Part 3, General Requirements, Volume-2 of Bid Documents.~~

17 ~~415 V Power capacitor and control panel~~

~~**18**~~

~~**19 Applicable Standards**~~

~~**20**~~

~~**21 The capacitor and control panel conform to the latest applicable standards specified below. In case of conflict between standards and this specification, this specification shall govern**~~

~~**22**~~

~~Shunt capacitors for power systems~~	~~IS : 13340~~
~~Internal fuses and internal overpressure disconnectors for shunt capacitors~~	~~IS : 12672~~
~~Metal enclosed switchgear~~	~~IS : 3427 / BSEN 60298 / IEC : 60298~~
~~Code of practice for phosphating iron and steel~~	~~IS : 6005/BS : 3189~~
~~Specification for copper rods and bars for electrical purpose~~	~~IS : 613~~

22.1 Design Features

22.2

22.3 The capacitor banks shall be complete with all parts that are necessary or essential for efficient operation. Such parts shall be deemed to be within the scope of supply whether specifically mentioned or not.

22.4

22.5 The capacitor bank shall be complete with the required capacitors along with the supporting post insulators, steel rack assembly, copper bus bars, copper connecting strips, foundation channels, fuses, fuse clips, etc. The steel rack assembly shall be hot dip galvanised.

22.6

22.7 The capacitor bank may comprise of suitable number of single phase units in series parallel combination. However, the number of parallel units in each of the series racks shall be such that failure of one unit shall not create an overvoltage on the units in parallel with it, which will result in the failure of the parallel units.

22.8

22.9 The complete capacitor banks with its accessories shall be metal enclosed (in sheet steel cubicle), indoor floor mounting and free standing type.

22.10

22.11 All sheet steel work shall be thoroughly cleaned of rust, scale, oil, grease, dirt and swarf by pickling, emulsion cleaning etc. The sheet steel shall be phosphated and then painted with two coats of zinc rich primer paint. After application of primer, two coats of finishing synthetic enamel paint oven baked/stoved, shall be applied.

22.12

22.13 The assembly of the banks shall be such that it provides sufficient ventilation for each unit. Necessary louvers may be provided in the cubicle to ensure proper ventilation.

22.14 Each capacitor unit/bank shall be fitted with directly connected continuously rated, low loss discharge device to discharge the capacitors to reduce the voltage to 50 volts within one minute in accordance with the provisions of the latest edition of IS : 2834.

22.15

22.16 Capacitors shall be of Mixed Dielectric of polypropylene and paper with internal element fuses. The impregnant shall be non PCB (poly chlorinated biphenyl) oil.

22.17

22.18 Each unit shall satisfactorily operate at 135% of rated KVAR including factors of overvoltage, harmonic currents and manufacturing tolerance. The units shall be capable of continuously withstanding satisfactorily any overvoltage upto a maximum of 10% above the rated voltage, excluding transients.

22.19

22.20 Unit Protection

22.21

22.22 Each capacitor unit shall be individually protected by an HRC fuse suitably rated for load current and interrupting capacity, so that a faulty capacitor unit shall be disconnected by the fuse without causing the bank to be disconnected. Thus, the fuse shall disconnect only the faulty unit and shall leave the rest of the units undisturbed. An operated fuse shall give visual indication so that it may be detected during periodic inspection. The fuse braking time shall co-ordinate with the pressure built up within the unit to avoid explosion. Mounting of the individual fuse may be internal or external to the capacitor case.

22.23

22.24 Power Capacitor and Control Panel

22.25

(a) Power capacitor and control panel shall be housed in metal enclosed cubicle. Power capacitor shall be housed in the lower compartment and capacitor control panel at top compartment.

(b) The control equipment including capacitors shall be mounted in a panel of cold rolled sheet steel. The panel shall be of indoor type and shall consist of :

(c) Busbars shall be of copper conductor of hard drawn (HD) and high conductivity

(d) Isolating switch

(e) Contactor with overload element

(f) Relays responsive to current/voltage/KVAR/PF as specified for automatic switching

(g)

(h) Sequencing devices, timers and auxiliary relays for automatic sequential switching of the capacitors in and out of the circuit.

(i) Auto-manual selector switches

(j)

(k) Push button for opening and closing the power circuit.

(l)

(m) Red and green lamps for capacitors ON/OFF indication

(n)

(o) Protective relays to protect the healthy capacitor units when one unit fails in a series connection

(p)

(q) Space heater and cubicle lighting as per the requirements.

(r)

(s)

(t) Drawings and Data

(u)

(v) All Drawings, data, technical particulars ,calculations, detailed literature, catalogues ,

(w) test certificates etc shall be submitted along with the bid/ after award of contract as

(x) specified under " Bid/Contract Drawings" , Part 3, General Requirements,

(y) Volume 2 of Bid Documents .

(z)

(aa) Diesel Standby Generator

22.26 Applicable Standards

The Diesel Standby Generator and its components shall conform to the latest applicable standards specified below :

Diesel Engines for GeneralPurposes	:	BS 5514 / ISO 3046
The Electrical Performance of	:	BS 5000

~~Rotating Electrical Machinery~~		
~~Rotating Electrical Machines~~	~~:~~	~~IS 4722~~
~~Circuit breakers~~	~~:~~	~~IS 13118, BS 5311, IEC 56 & 694, BSEN-60942 (P-2)~~
~~Air break switches air break disconnectors, air break switch disconnectors and fuse combination units for voltage not exceeding 1000 V AC or 1200 V DC~~	~~:~~	~~IS 13947 (P 3), BS EN60947, IEC-60947-3~~
~~Current transformer~~	~~:~~	~~IS 2705/BS 7626, IEC 60185~~
~~Voltage transformer~~	~~:~~	~~IS 3156/BS 7625/IEC 60186~~
~~Electrical Relays~~	~~:~~	~~IS 3231, 3842/BS 142/IEC 60255~~
~~Contactors for voltage not exceeding 1000 V ac or 1200 VDC~~	~~:~~	~~IS 13947 Part IV/ BSEN 60947-4-1/ IEC 60947-4-1~~
~~Control Switches~~	~~:~~	~~IS 6875/BSEN 60947 / IEC 60947-4-1~~
~~High Voltage Fuse~~		~~IS 9385/BS 2692/ IEC 60282~~
~~Low Voltage Fuse~~	~~:~~	~~IS 13703/BS 1362 IEC 269-1~~
~~Electrical direct acting indicating instruments~~	~~:~~	~~IS 1248/BS 89/IEC 60051~~

A.C. electricity metres of induction type voltage greater than1000 volts	:	IS722, 8530/BS 5685 / IEC 60145, 60211
Resistance wire, tapes and stripes for heating elements	:	IS 3725
Wrought aluminium and aluminium alloy bars, rods, tubes and sections for electrical purposes	:	IS 5082
Specification for copper rods and bars for electrical purposes	:	IS 613
Toggle switches	:	IS 3452/BS 3676
Control switches/push buttons	:	IS 6875/BSEN 60947
Noise and Emission Limit	:	As per latest notification of ministry of Environment and Forests

22.27 General Requirements

The diesel engine and generator shall be skid mounted and shall be located in a room near Treatment plant substation building. The diesel engine shall draw cooling air directly from outside the room through a weatherproof, acoustically treated duct. The exhaust system shall be insulated to minimise the amount of heat entering the room and to prevent injury to personnel. The silencer shall be of the 'residential' type and be located externally.

The generation voltage shall be 415V for D.G capacity less than 2MVA and generation voltage shall be 11kV for D.G capacity more than 2MVA. In case more than one D.G set is required for achieving the required capacity they shall be operated in parallel with necessary synchronizing arrangement. At no point D.G sets will be operating parallel with grid.

~~The diesel engine fuel shall be stored in an above ground bulk storage steel tank to be located adjacent to the generator room at a site accessible for filling to local road tankers. The storage tank shall be sized to store fuel for 1 day running of the engine at full load. The tank shall be provided with fittings to permit the visual observation of fuel level and filling by local tanker operators. A level meter shall also be mounted in the tank so that remaining fuel volume can be monitored at the generator / substation PLC and the operator stations in the SCADA room.~~

~~The fuel storage tank shall be located in a bund capable of holding not less than 125 % of the maximum storage tank contents. Fuel transfer pumps shall be provided to automatically transfer fuel from the bulk storage tank to a high level 990 litres day tank located in the generator room or generator skid mounted day fuel tank. A semi-rotary hand pump shall be provided to permit transfer of fuel in the event of a failure of the transfer pump. Any leakage from the pumps shall be routed to the bund.~~

~~A system shall be provided within the generator room to detect fire, to raise a local audible alarm (manually silenced locally) and if a high level day tank is used, to automatically dump the day fuel back to the bulk storage tank.~~

~~The system shall be constructed such that leakage of water, fuel or oil within the generator room shall be routed to a local sump where a detector shall be provided to raise an alarm.~~

-

~~The system shall be constructed such that the leakage of fuel or the accumulation of water within the fuel storage bund shall be detected and shall raise an alarm.~~

~~All alarms shall be conveyed to the central HMI through the PLC.~~

~~Diesel Generating Set Automatic Control~~

~~AMF Diesel Generator Set capable of automatic starting and picking the load within 30 seconds shall be provided to cater for emergency loads and lighting during mains power failure . Diesel generating set for use in auto mains failure mode shall have a three position automatic / off / manual selection and shall operate as follows :~~

~~Automatic mode :~~
~~On occurrence of mains failure the following sequence shall be followed.~~

~~a) Mains to Generator changeover~~
~~mains failure detected~~
~~delay of 10 seconds~~
~~generator is started and run up to speed~~
~~time delay of 50 seconds~~
~~mains supply is switched off~~
~~generator supply is switched on~~
~~b) Generator to Mains changeover~~
~~mains healthy detected~~
~~manual changeover signal received,~~
~~generator supply is switched off~~
~~mains supply is switched on~~
~~generator runs for 2 minutes and stops~~

~~All timer settings shall be adjustable~~

~~If mains power is restored during the initial one minute delay then the power shall be~~
~~monitored for a further one minute and if it is still healthy, mains power shall be restored.~~
~~The generator shall be stopped after a further 2 minutes of running on no load. If the~~
~~generator fails to start after an initial period of cranking, two further attempts shall be~~
~~made with an appropriate interval between each attempt. If the engine fails to start after~~
~~three attempts the system shall shut down and a local and remote alarm shall be~~
~~annunciated.~~

~~Manual mode:~~

- The generator shall run to the dictates of manual controls on the generator. No automatic changeover of mains to generator supply or vice versa shall take place. The generator shall be loaded by manual switching if required.

- Alternator for Diesel Generating Set

- Alternator shall be 4 pole, 3 phase 11kV,50 Hz, 0.8 P.F , salient pole, revolving field,
- brushless type, self-regulating continuously rated and manufactured in accordance with IS
- 4722, BS 5000 : Part 99 or IEC 60034-1. They shall be totally enclosed, screen protected,
- fan ventilated and vertical drip proof conforming to IP 23.The Alternator shall be
- complete with excitation system , AVR and all necessary auxiliaries. The alternator shall
- be driven by diesel engine detailed below and shall match the same in all respects. The
- terminal box shall be dustproof with IP 54 degree of protection . The terminal box shall
- be suitably sized to terminate the size and number of cables involved.

- Alternators shall be capable of withstanding a 10% overload for 1 hour in any 12 hour
- Period under the specified conditions of temperature, humidity and atmospheric pressure.
- Alternator windings shall be of Class H insulation with Class F temperature rise and
- tropicalised. The alternator shall have prepacked grease lubricated ball or roller bearings
- and provided with facilities for regreasing whilst in service.
- The alternator shall be foot mounted on a common bedframe with the primemover close

- coupled to the engine flywheel housing. The direction of alternator rotation when viewed
- from the driven end shall be clockwise and phase voltage sequence UVW. The alternator
- vibration level shall not exceed the values defined in IS 12075.
-
- The alternator shall be capable of maintaining a short circuit current of three times full load
- current for a period of 10 seconds. The alternator shall be fitted with an anti condensation
- heater. No individual harmonic shall exceed 1% and the total harmonic shall not exceed
- 3%. The alternator, its neutral and control panel shall be earthed as per relevant standards .
- The alternator rotor assembly shall comprise exciter rotor, full wave silicon bridge rectifier,
- surge protection device and salient pole rotating field system. The rotor shall be fitted with
- interconnected pole face damping windings. Voltage regulation shall be maintained to
- within ±2.5% for a power factor of 0.8 to unity, including hot to cold variations. The steady
- state frequency droop between no load and full load shall not exceed 5%.Transient voltage
- deviation following a step load of 60% of rated at a power factor of between 0.4 and zero
- shall not exceed 15% with a voltage recovery time to 97% rated voltage not exceeding 0.5
- second.The set shall be capable of continuous operation with a phase current imbalance of
- 33% of rated current whilst maintaining the output voltage within ±5% of rated.
-
- Diesel Engine for Generating Set
-

- Engine shall be four stroke, direct injection, turbocharged industrial machines. They shall
- be fitted with renewable wet cylinder liners if water cooled and shall be direct coupled to
- the alternator and mounted on a common rigid steel bedplate.
-
- Engines shall be rated for continuous duty at site ambient conditions with an inherent O/ L
- Capacity of 10% for 1 hour in any 12 hours. The engine shall be capable of running at full
- load for not less than 180 hours without maintenance adjustments and 10 000 hours

between major overhauls. The maximum operating speed shall be 1 500 rpm.The range of
manual adjustment shall not be less than ±5% of rated speed. The performance of engine
governors under load conditions shall be to Class A2 in accordance with BS 5514 : Part 4.
Engine governors shall be suitable for remote control load sharing between identical
engine units. In addition to any electrical overspeed trips, there shall be a mechanical
overspeed device which shall operate at 120% of the rated speed. Re-setting of the
overspeed trip shall be possible by hand only.The steady state output speed drop between
no load and full load shall not exceed 5%. The transient output speed deviation
shall not exceed 10% for a step of 60%. Engines shall be designed to run on fuel oil
complying with IS 1460 or BS 2869, Class A2.Engines shall be cooled by means of a
water jacket, heavy duty air blast radiator with integral radiator header tank, circulating
pump and engine driven pusher type fan. The fan shall draw air in from the vicinity of the

engine block and discharge it through the radiator core. The radiator shall be mounted on the same bedplate as the engine and alternator on suitable vibration isolators and be arranged so that it is located directly behind automatic louvers set into the external wall of the engine room. A thermostatically operated by-pass valve shall be fitted in the cooling system to maintain an optimum operating temperature during starting and running conditions. Drain cocks shall be provided so that all the water can be drained from the system.A separate oil cooler shall be used for cooling the engine oil. A thermostatic by-pass valve shall be incorporated.Engine lubrication shall be by a closed circuit wet sump, forced feed system supplied by an engine driven pump fitted with pressure regulating and relief valves, sump suction filter and changeover renewable micro-felt full flow line filters. A hand operated semi rotary oil pump shall be installed to carry out initial priming or to fill or empty the sump as required. The sump shall be fitted with an easily accessible drain point. The oil shall be of the grade recommended by the engine manufacturer.The starting system shall comprise 12 or 24 V heavy duty lead acid batteries (positioned on a floor mounted stand adjacent to the engine) connected by heavy duty flexible butyl rubber cables. Batteries shall be sized to give six consecutive starts of the engine at 0°C. An engine driven alternator and charging system shall be provided. An automatic mains energised battery charger shall be provided, with sufficient capacity to

~~maintain the battery in a condition to fulfil the starting requirements. Barring (hand turning) equipment shall be provided so that the engine can be manually rotated for maintenance purposes. It shall be arranged so that normal starting of the engine is inhibited whilst the hand turning equipment is connected. Twin heavy duty air intake filters in accordance with IS 3169 or BS 7226 suitable for operating in dust laden atmospheres shall be fitted. The filters shall be of the paper element with pre-cleaner type. Turbocharger filters shall be fitted. Breathers shall be fitted with washable filters which are easily accessible for maintenance.~~

~~Instrumentation shall be provided to monitor speed, oil pressure,oil temperature (sets larger than 250 kVA), water temperature and battery charge current. The bedplate shall be of heavy gauge steel construction, stress relieved and free from distortion.~~

~~Machined surfaces shall be incorporated for mountings and for levelling.Anti-vibration mountings shall be fitted between the bedplate and the floor to prevent vibrations being transmitted to the building. The mountings shall be adjustable for levelling purposes and shall be designed to resist horizontal movement of the diesel set.~~

~~The fuel System shall comprise an engine driven feed pump with duplex filters, 990 litres day tank with supporting structure or generator skid mounted day fuel tank, with all interconnecting pipe work , flexible engine connection pipe etc.~~

~~Diesel Generator Control Panel :~~

~~The control panel shall be separately mounted on anti vibration mountings and shall~~

~~Comprise the following :~~

~~- Breaker incorporating short circuit and overload trip~~
~~- Earth fault protection for the Alternator~~
~~- Alternator Over & Under Voltage Protection~~
~~- Voltage Controlled Over Current Relay~~
~~- voltmeter and seven position selector switch~~
~~ammeter and 4 Position selector switch~~
~~frequency meter~~
~~Power Factor Meter~~
~~Kwh Meter~~
~~engine temperature and oil pressure gauge~~
~~service hours run indicator~~
~~key switch start and stop control~~
~~operational status indicator~~
~~anti-condensation heater and thermostat~~
~~alternator anti-condensation heater controls~~
~~mains fed battery charger~~
~~Auto start on mains power supply failure facility~~
~~Fails to Start (Alarm)~~
~~Over / Under Voltage Alarm~~
~~Battery Charger Fault (Alarm)~~
~~Low fuel Oil Level (Alarm)~~
~~Over Load (Alarm)~~
~~Low Lube Oil Pressure (Trip)~~
~~High Water Temperature(Trip)~~
~~High Lube Oil Temperature (Trip)~~
~~Electrical Protection Relays (Trip).~~

~~A reset button shall be provided to cancel the alarm /shut-down condition prior to re-starting.~~

~~Simple operating instructions shall be detailed on the fascia of the control panel.~~

~~Synchronising Panel~~

~~Whenever two sets are required to operate together , necessary synchronising panel complete with circuit breaker ,synchroscope , relays ,meters etc shall be provided. The Panel shall be floor standing ,CRCA Sheet steel enclosed .~~

~~Acoustic Enclosure~~

~~(i) The DG Set shall be provided with acoustic enclosure, fully integrated , weather proof with superior finish for long and durable life.~~

~~(ii) The acoustic enclosure shall be CRCA sheet steel enclosed with necessary panels and doors, inside lining of fire retardant foam /glass wool as acoustic material.~~

~~(iii) The sound level shall be restricted to 75 dB at a distance of 1 meter, under full load, free field conditions as per relevant standards.~~

~~(iv) The acoustic enclosure shall be certified to meet the emission norms.~~

~~Bulk Fuel Storage Tanks~~

~~Tanks and fittings, etc shall conform to IS 803 or BS 799 : Part 5. The tank shall be constructed in mild steel and the fittings in materials other than:~~

~~Yellow brass, including low grade alloys of copper and zinc.~~

~~Lead and zinc.~~

~~Galvanised metals.~~

~~Natural rubber.~~

~~An ullage volume above maximum contents level of the tank shall not be less than 5% of the maximum volume of the fuel. The maximum fuel surface level below the point of entry of the vent shall not be less than 100 mm. The internal surface shall be cleaned and treated with temporary preservative, soluble in fuel oil, before shipment.~~

The following fittings shall be included:

600 mm diameter manhole complete with portable cover situated in the top of the tank
complete with ladder to the interior.
Dipstick, calibrated in litres with guide tube and striker plate.
Local indication of fuel level to be given at a position where it can be easily read during
fuel delivery.
Filling pipe work and fittings complete with isolation valve and captive end cap. The filling point to be at the top of tank to prevent siphoning.
Outlet pipe situated at the raised end of the tank not less than 150 mm above tank bottom, complete with check valve, isolating valve and end cap.
Drain pipe situated at lowest point in tank complete with isolating valve and captive end cap.
Inlet fittings for overflow pipe from daily service tank or tanks (where specified).
Vent pipe situated at high level in the tank. The pipe shall rise continuously from the tank and terminate with an inverted `U' bend and vermin screen.
External ladder for horizontal tanks more than 2 m diameter.

Drawings

All Drawings, data, technical particulars ,calculations, detailed literature, catalogues ,
test certificates etc shall be submitted along with the bid/ after award of contract as
specified under " Bid/Contract Drawings" , Part 3, General Requirements,
Volume-2 of Bid Documents .

Battery, Battery Charger and D.C Distribution Board

DC equipment shall comply with IEC 60896 including those standards referred to therein.

~~Requirements~~

~~Following items shall be covered in the Contract:~~

~~a) One no. 110 V Nickel Cadmium type Battery (Minimum capacity of Battery – 75AH)~~

~~b) One no. Float-cum-boost charger for 110 V battery~~

~~c) DC distribution board.~~

~~All connections between battery, battery chargers and DC distribution board shall be designed for effective segregation between positive and negative leads.~~

~~Nickel – Cadmium Battery~~

~~6.9.1.1 Design Features~~

~~(a) Battery offered shall be Nickel Cadmium (Ni Cd) Type. The battery shall conform to the latest applicable standards specified below:~~

~~Specification for vented type : IS 10918~~
~~Nickel Cadmium Batteries~~

~~(b) Nickel hydroxide and Cadmium hydroxide shall be used for positive and negative electrode respectively. Aqueous solution of battery grade Potassium hydroxide with small quantities of lithium hydroxide shall be used as electrolyte. It shall be used only for ion transfer and shall not chemically change during charging/ discharging.~~

~~(c) The containers shall be transparent and preferably be made of toughened glass or plastic polypropylene material and provided with electrolyte level indicator. The Containers shall be robust, heat resistant, leak proof, non absorbent and free from crack, blisters, pin hole etc.~~

(d) The battery shall be rated on 5 hour basis and for the specified ambient temperature. The battery shall have maximum recharge time of 8 hours.

(e) Terminal posts shall be designed to accommodate external bolted connection conveniently and positively. Each terminal post shall have two bolt holes of the same diameter, preferably at right angles to each other. The bottom hole shall be used to terminate the inter-cell connection. The top hole shall be left for external terminal connections. Bolts, heads and nuts, except seal nuts, shall be hexagonal and shall be lead covered. The junction between terminal posts and cover and between cover and container shall be so sealed as to prevent any seepage of electrolyte.

(f) Required quantity of electrolyte for first filling with 10% extra shall be supplied in non returnable containers.

(g) Each battery shall be complete with following accessories, as applicable, that include, but are not limited to:

i) Battery racks

ii) Porcelain insulators, rubber pads, etc.

iii) Set of inter-cell, inter-tier and inter-bank nickel coated copper connectors as required for the Complete installation.

iv) Electrolyte for first filling + 10% extra.

1 set of accessories for testing and maintenance shall also be provided suitable for all the three battery banks.

	One	3, 0, +3 volts DC voltmeter with built in discharging resistor and suitable leads for measuring cell voltage.
ii.	One	Filler hole thermometer fitted with plug and cap and having specific gravity correction scale.
iii.	Three	Pocket thermometers
	Two	Cell lifting straps
	One	Terminals and cable boxes with glands for

set	connecting cable as required.
Each of	Spare connectors Spare vent plugs Spare nuts and bolts Suitable set of spanners

(h) Each battery shall be mounted in a manner that permits easy accessibility to any cell. The racks shall be suitable for fixing on flat concrete floor. The complete racks shall be suitable for bolting end to end.

(i) It shall be the responsibility of the Contractor to provide batteries of adequate capacities to meet specified requirements pertaining to control, indication, annunciation, etc. and emergency lighting. For computing battery capacity, it shall be assumed that the battery is fully charged at the beginning of loading cycle and is discharged to a voltage of 1.2 volts per cell at the end of the loading cycle. The battery shall have minimal difference (approx. 0.3 V per cell) between float and boost charging voltages.

(j) The following information shall be legibly marked on outside each cell.

- Manufacturer's Name & Trade Mark
- Country & Year of Manufacture
- AH Capacity at 5 hour discharge rate
- Type Designation & Sl.No

6.9.1.2 Drawing

All Drawings, data, technical particulars ,calculations, detailed literature, catalogues , test certificates etc shall be submitted along with the bid/ after award of contract as specified under " Bid/Contract Drawings" , Part 3, General Requirements,

~~Volume 2 of Bid Documents .~~

~~Battery Charger and D.C. Distribution Board~~

~~6.9.2.1 Applicable Standards~~

~~The battery charger and D.C. distribution board shall conform to the latest applicable standards specified below. In case of conflict between the standards and this Specification, this Specification shall govern.~~

~~Basic climatic and mechanical durability tests for components for electronic and electrical equipment~~	~~:~~	~~IS:9000~~
~~Environmental tests for electronic and electrical equipments~~	~~:~~	~~IS:9000~~
~~Metal clad base material for printed circuits for use in electronic and telecommunication equipment~~	~~:~~	~~IS:5921~~
~~Transformers and inductors (power, audio, pulse and switching) for electronic equipment~~	~~:~~	~~IS:6297~~
~~Printed wiring boards~~	~~:~~	~~IS:7405~~
~~Environmental requirements for semi-conductor devices and integrated circuits~~	~~:~~	~~IS 6553~~
~~Terminals for electronic equipment~~	~~:~~	~~IS:4007~~
~~Factory built assemblies of switchgear and control gear for voltages upto and including 1000 V AC and 1200 V DC~~	~~:~~	~~IS:8623/BS: 5486 / IEC:60439~~

~~Air break switches : IS : 13947 (Part 3)BSEN 60947-3~~

~~Miniature circuit breakers : IS 8828/BSEN:60898~~

~~HRC cartridge fuses : IS:9224/BS:88~~

~~Contactors : IS:13947 (Part 3) /BS:775 / IEC:60158-1~~

~~Control switches/push buttons : IS:6875~~

~~Indicating instruments : IS:1248/BC:89/ EC:51~~

~~Degree of Protection : IS:13947 (Part 1) /IEC:60947-1~~

~~Climate proofing of electrical equipment : BSCP:1014~~

~~Code of practice for phosphating iron and steel : IS:6005/BS:3189~~

~~Semi conductor converters : IEC:60146~~

~~Semi conductor rectifier equipment safety code : IS:6619~~

~~Specification for copper rods and bars for electrical purposes : IS : 613~~

~~6.9.2.2 Battery Charger~~

~~Battery charger shall be combined float-cum-boost type.~~

~~The charger shall be static type composed of silicon controlled rectifiers (SCRs) and diodes connected in three phase full wave half controlled bridge circuit.~~

~~The rectifier transformers for float and boost chargers shall be indoor dry type, double wound with delta star connections. The BIDDER shall ascertain if taps are required and provide adequate number of primary and secondary taps, if necessary.~~

~~The float charger shall be designed for supplying :~~

~~The D.C continuous load and short time overload.~~

~~The trickle charging current of the battery.~~

The boost charger shall be designed for supplying the boost charging current of the battery.

If the battery and charger are to be supplied by separate contractors, the charger Contractor shall coordinate with the battery contractor regarding float /trickle boost charging current & voltages required for the battery.

Battery Charger shall be provided with facility for both automatic and manual control of output voltage and current and necessary selector switch shall be provided. Contractor regarding the float/trickle and boost charging current and voltages required by the battery,

Performance

Float Charger

The D.C. output voltage during float charging shall be stabilised within

±1% of the set DC bus voltage. Manual control shall be used if auto mode fails.

Boost Charger

For boost charging the discharged battery after a mains failure, the rectifier shall charge the battery at high rate limited to the maximum boost charging voltage. After a specified number of hours (adjustable) when the rated cell voltage is reached, the charger shall be returned to float charge status.

In case of combined float-cum-boost charger, the switching and control of high rate charge and return to float charge shall be by automatic controller/regulator. Manual control shall be used if auto mode fails.

During boost charging following emergency measures shall be provided:

If the AC mains supply fails, an arrangement shall be made to automatically connect the battery directly across the load.

If the separate or spare float charger supplying D.C. load fails, the load shall be fed from the point of connection at the tapping of the battery via adequately rated blocking diodes.

(iii) Suitable filter Circuits shall be provided in the chargers to limit the ripple content (peak to peak) in the output voltage to 1% irrespective of D.C Loads.

(j) The D.C System shall be unearthed.

~~6.9.2.3 Charger Panel and D.C. Distribution Board~~

~~Battery charger panel and D.C. distribution board shall be sheet metal enclosure free standing type with cable entry from bottom.~~

~~Indications, controls and output voltage setting adjustments shall be on front panel. The Contractor shall submit a scheme for alarm and trip indication lamps on the cabinet and for fault annunciation contacts paralleled for remote annunciation.~~

~~The components shall be liberally rated and housed in a well ventilated sheet metal cubicle complete with input and output terminals. Louvers shall be provided for ventilation backed up by fine wire mesh so that the degree of protection shall be equal to or better than IP 42.~~

~~Busbars shall be of copper conductor of hard drawn (HD) and high conductivity. Busbars shall be fully insulated by encapsulation in epoxy resin with moulded caps protecting all joints~~

~~All printed circuit cards shall be plug in type, interlocked to prevent insertion in a wrong slot. Each card shall have LED indication on its front plate to indicate normal condition and readily and marked test pins.~~

~~All components shall be accessible to the maintenance technician for easy disassembly and replacement. Access to parts of equipment shall be with minimum danger from all hazards.~~

~~All components and modules shall be clearly and unambiguously marked and all wiring colour-coded and tagged.~~

~~All power and control wiring within the cubicle shall be done with stranded copper wires. The power wiring shall be adequately sized for the required rating. The minimum sizes for control wiring will be 1.5 mm^2 and for power wiring shall be 2.5 mm^2.~~

~~Ground terminals with isolating links shall be provided.~~

~~Cable glands shall be provided to suit the incoming and outgoing cables.~~

~~6.9.2.4 Components/Accessories~~

~~The main items are listed below. However, additional items required for completeness or to meet the specified performance or operational requirements of the charger, shall be deemed to be included in the Contractor's scope. Instead of incoming ON/OFF switches, stricker fuses and contactors, the~~

~~Contractor may provide suitably rated 3 pole MCBs with overload and short circuit protection and auxiliary contacts.~~

~~One (1) set - Three phase full wave half controlled bridge rectifier circuit comprising silicon controlled rectifiers and silicon diodes complete with resistor/capacitor network for surge protection. The diodes/SCRs shall be individually protected by fuses with fuse fail indication.~~

~~One (1) Double wound, dry type, three phase suitably rated mains transformer.~~

~~One (1) set of suitably rated control transformers for electronic controller.~~

~~One (1) Electronic controller comprising of power supply card, soft start cum current limit card, auto trickle mode card with facility for setting trickle charge current and monitoring battery current, error amplifier cards and pulse generating cards for achieving the DC output voltage stabilisation of ±1% and also for achieving current limiting feature. The electronic controller shall have protection features with indications for under voltage, over voltage, set output voltage and phase failure or voltage unbalance.~~

~~The electronic controller shall be provided with following features.~~

~~Boost current stabilisation of ±2% with AC input variation of voltage and frequency variation of ±10% and ±5% respectively.~~

~~Boost charge current limiter with potentiometer to adjust the setting.~~

~~Adequately sized necessary built-in accessories shall be provided such that on failure of the controller in auto mode the voltage can be effectively controlled manually.~~

~~One (1) Filter circuit comprising of smoothing choke and condensers complete with HRC fuse with trip indication for filter condenser circuit.~~

~~One (1) Auto/Manual selector switch for selecting the mode of operation of the controller.~~

~~One (1) front panel mounted potentiometer for set point adjustment of output voltage in auto mode.~~

~~One (1) front panel mounted potentiometer for manual adjustment of voltage in manual mode.~~

~~One (1) TP AC ON/OFF switch for float charger incoming.~~

~~One (1) set of HRC fuses complete with fuse fittings for AC input with suitable ratings and with trip indication.~~

~~One (1) set of the pilot lamps with series resistors to indicate float charger AC Mains 'ON' condition.~~

~~One (1) AC contactor with suitably rated coil and three main and 2 NO + 2 NC auxiliary contacts, suitably rated thermal overload relay and ON/OFF control switch.~~

~~One (1) set of HRC fuses complete with fuse fittings for the DC output, and with trip indication.~~

~~One (1) moving coil DC ammeter, with shunt, of size 96 x 96 mm and suitable range to read the float charger output current.~~

~~One (1) Double pole DC ON/OFF rotary switch for float charger output.~~

~~One (1) pilot lamp with series resistor to indicate float charger DC 'ON' condition.~~

~~Annunciation System for the following~~

~~(a) AC Supply Failure.~~

~~(b) Rectifier Fuse Failure.~~

~~(c) Surge Circuit Fuse Failure.~~

~~(d) Filter Fuse Failure.~~

~~(e) Load Limiter Operated.~~

~~(f) Charger Trip.~~

~~(g) Battery on Float.~~

~~(h) Battery on Boost.~~

~~6.9.2.5 Power Electronic Components~~

~~(a) Diode and thyristors shall be of monocrystalline type silicon, capable of continuous output at specified voltages. It shall have high power efficiency.~~

~~(b) If many diode or thyristor assemblies are connected in parallel, care shall be taken to ensure that each rectifier or thyristor operates within its rating and shares the load uniformly. This may be achieved with the help of chokes. Also, care should be taken to select matched pairs of rectifier heat sink units.~~

~~(c) Each diode or thyristor built in a multi built assembly shall be provided with a short circuit protection to avoid complete shut-down of the equipment because of a fault on single unit. Suitable fuses shall be provided for such protection.~~

~~(d) Necessary spare capacity shall be built in the equipment to continuously supply full load even with one unit out of circuit.~~

~~(e) The diodes or thyristor banks shall be natural air cooled.~~

~~(f) The diodes or thyristors shall be protected against overvotage due to chopping surges with the aid of snubbers (i.e. resistor-capacitor combination and Metal oxide varister). It shall be ensured that normal load currents and especially fault currents are shared equally between parallel links, within the specified limits. To achieve this, great care shall be taken to design the layout of the rectifier links to ensure equal lengths of busbars and as near as possible identical contact resistance in each current path.~~

~~(g) 6.9.2.6 Drawings and Data~~

~~(h) All Drawings, data, technical particulars ,calculations, detailed literature, catalogues ,~~

~~(i) test certificates etc shall be submitted along with the bid/ after award of contract as~~

~~(j) specified under " Bid/Contract Drawings" , Part 3, General Requirements,~~

~~(k) Volume 2 of Bid Documents.~~

~~(l) Variable Frequency Drives~~

~~(m)~~ **2.5 Variable Frequency Drives**

2.5.1 Applicable Standards

a) Specification for metal clad base ~~IS:5921~~ ~~m~~materials for printed circuits for use in electronic and telecommunication equipment - IS:5921

~~b) Specification of Transformers and IS:6297~~ ~~I~~Inductors (Power, Audio, Pulse and Switching) for Electronic Equipment - IS:6297

~~c) Semiconductor rectifier equipment IS:6619~~ safety code ~~for~~ - IS:6619

~~d) Specification for printed wiring IS:7405~~

Board - IS:7405

e) Recommended practice for emerg- IEEE :446 ency and standby power systems for industrial and commercial application. - IEEE :446

f) Semiconductor devices - IS:3700

g) Basic climate for mechanical IS:9000 ddurability tests for electronic Components - IS:9000

h) Environmental requirements of semiconductor IS:6553 i) devices and integrated circuits- IS:6553

j) Ambient temp. of electronic Equipment - IS:9676 Equipment

k) Terminal for electronic equipment - IS:4007

2.5.2 Configuration

Frequency drivess shall have one of the two configurations given below:

a) Current source inverter.
b) Voltage source inverter.

(a) Smoothing Reactors for Current and Voltage Source Inverter

a) The smoothing reactor shall be sized to avoid conditions of discontinuous current

b) Operation of the frequency converter at its lowest frequency of operation, which shall not be less than 5 Hz.

c) The smoothing reactor shall be uniformly insulated and shall be protected for voltage surges occurring during sudden load throw-off.

d) The smoothing reactor shall be made from electrolytic grade copper/aluminium and shall be epoxy encapsulated with suitable class of resin decided from techno-economic considerations and performance requirements in conformity with IEC-146.

2.5.3 Inverter

The inverter system suitable for three phase output shall consist of the following

subsystems:

a) The basic inverter circuit consisting of the switching device say

b) Thyristors/Transistors/IGBT/MOSFET, connected so as to supply three phase

c) power.

d) The logic network to enable rapid transition of the main inverter switching devices from on-state to off-state.

e) Suitable feedback system to allow balance of reactive power flow during load

power factor fluctuation as well as regeneration.

f) The filter system of the inverter output to supress 5th, 7th, 11th, 13th harmonics at the output of the inverter to less than 5% of the fundamental amplitude.

g) The ripple control system to limit current ripple to 4% at the input terminals of the inverter caused by distorted current output.

The output frequency of inverter shall be controlled to within the limits.

2.5.3.1 Inverter for AC drive

Current Source Inverter

a) Constant Torque Operation

The current output by the DC link shall be accurately monitored so that the ratio of the terminal voltage of the motor and the corresponding frequency remains constant. Necessary protective features for tripping the frequency converter, alarm/annunciation and fault diagnostics shall be provided.

b) Constant Horsepower Operation

In this type of operation, the motor's internal voltage shall be maintained within + 1% while the frequency of the inverter is varied to meet the duty cycle requirements. Necessary protective features for tripping the frequency converter, alarm/annunciation and fault diagnostics shall be provided.

Voltage source Inverter

a) Constant Torque Operation

The DC voltage input to the inverter shall be accurately monitored to maintain the ratio the terminal voltage of the motor to frequency at the rated/design value. The DC voltage input shall be maintained within + 1% of the required value. Should this fall for any reason, necessary action for tripping the frequency converter, and initiation of annunciation/alarm and fault diagnostic shall be provided.

b) Constant Horsepower Operation

In this type of operation, the voltage at the terminals of the motor shall be maintained within +1% of the rated value while the frequency of the inverter is varied to meet the duty cycle requirements. Necessary protective features for tripping the frequency converter , initiation of alarm/annunciation and fault diagnostic shall be provided.

Output Overcurrent Limit

Unless otherwise stated, the inverter shall be capable of being temporarily overloaded to 150% of its full load ampere capacity for sixty (60) seconds beyond which a current limit action shall be initiated and an alarm contact initiated for annunciation.

Control Modules

All elements of the control system shall be mounted on epoxy laminate boards and each board shall be a plug in module mounted on a standard nineteen inch rack which shall be accessible from the front. Each card shall have LED indication on its front plate to indicate normal condition of the card. Readily accessible and clearly marked test pins shall be provided at the important points on the cards to enable signal analysis.

The epoxy laminates shall be free from manufacturing errors and shall be designed to prevent incorrect insertion in the card rack. The copper side of the card shall be suitably lacquered to prevent oxidation. The gap between two cards shall be sufficient to permit adequate ventilation.

Adjustments susceptible to change by accidental contact shall be lockable.

2.5.4 Control Requirements

Short time voltage dips upto 80% of nominal (e.g. in case of large motor start-up connected to same bus) shall not cause the control system to stop functioning and shall not trip the drive system.

The drive motor shall be speed regulated corresponding to 4-20mA or 0-10V reference input signal. Upon complete loss of users speed reference signal, the drive shall automatically run at constant speed as determined by the last speed reference available prior to loss of the signal.

The required provision for interfacing with PLC/DCS, including details of communication module and data transfer facility, I/O details shall be furnished by the Bidder.

2.5.5 Protection

Protection of Power Semiconductor

a) Each power semiconductor shall be protected against short circuit. The fuse shall be sized so that its I^2t does not exceed the I^2t characteristic of the power semiconductor itself. The voltage and current rating of the fuse shall match the duty on the power semiconductor. The arc voltage, due to melting of the fuse shall not exceed the repetitive peak reverse voltage of the power semiconductor.
b) All fuses shall have a trip indicator to operate a suitable microswitch with at least 1 NO + 1 NC potential free contacts for annunciation and/or tripping.

c) A fast tripping feeder circuit breaker shall be used in case fuses for short circuit protection of thyristors are not used.

Protective Systems for AC Inverter Drive

a) Fuses for all power semiconductors and/or other devices like commutation chokes, capacitors etc. which are not adequately protected against flow of abnormal currents.
b) Under voltage and over voltage protection on the input side. Loss of input voltage to inverter shall entail tripping of the inverter.
c) Protection for all control cards, power supply stabilisers, filter circuits etc. Protection shall be provided such that failure of a part does not cause damage elsewhere in the system.
d) Polarising relay to prevent reversal of polarity on the input side of the inverter.
e) Protection of inverter thyristor, commutating circuits and other inverter elements during regenerative operation of the inverter and also during sudden load throw-off.
f) Current limit fuses at the output of the inverter.
g) Commutation circuit undervoltage
h) Inverter overfrequency
i) Programmable overcurrent
j) Phase sequence/loss of phase protection
k) Earth fault protection
l) DC link overvoltage protection
m) Specific motor protection
n) Incoming line surge protection
o) Ventilation Loss
p) Over temperature

2.5.6 Cooling Of Power Converters

Power semiconductors shall be mounted on heatsink which can be individual or common to a number of devices. Adequate provision for clamping and mounting the power semiconductors shall be available.

Cooling of power semiconductors can either be natural air cooled or forced air cooled. The BIDDER shall recommend the type of cooling. However, for power converters which exceed capacities of 2 kA continuous load, alternative cooling methods as oil or water cooling shall be considered. The power semiconductors shall preferably be double side cooled.

2.5.7 Switching Devices

Switching devices such as circuit breakers, isolators, contactors; switch-fuse units etc. shall be considered in the scope of supply.

The switching devices shall be enclosed in a separate enclosure forming the set of panels for the power converters. They shall have adequate clearance both with adjacent devices and metalwork at earth potential. Connection between devices shall be by adequate size of electrolytic grade of copper/aluminium strips. These connections shall be adequately braced and insulated.

2.5.8 Constructional Features

The controller should have modular construction to facilitate maintenance.

Bus bars

Power connections shall be of the bolted type and mating surfaces shall be tinned.

The bus bars running to various converters shall be suitably designed to ensure equal sharing between the parallel strings and prevent mechanical stress on the fuse.

All bus bars shall be adequately insulated for full circuit voltage by insulating tapes and similar insulating material.

In case aluminium bus bars are specified, care shall be taken to ensure that bimetallic connections are provided wherever necessary.

All cubicles shall have copper earth buses of adequate size running the entire cubicle height along the sides.

Cubicle

Cubicles housing the power semiconductors and drive level control system shall conform to IP 42 degree of protection to enclosures.

Panels shall be free standing, floor mounting type and shall comprise rigid welded structural frames enclosed completely with cold rolled sheet steel of

thickness no less than 2.5 mm for front and rear portions and 2.0 mm for sides, top and bottom portions. There shall be sufficient re-inforcement to provide level surfaces, resistance to vibrations and rigidity during transportation and installation.

All doors, removable covers and panels shall be gasketed all round with neoprene gaskets. Ventilating louvers shall have screens and filters. The screens shall be made of either brass or GI wire mesh.

Design, material selection and workmanship shall be such as to result in a neat appearance inside and outside with no welds, rivets or belt heads apparent from outside, with all exterior surfaces true and smooth.

Painting

All sheet steel work shall be phosphated in accordance with the following procedure and in accordance with IS: 6005 "Code of Practice for Phosphating Iron and Steel".

Oil, grease, dirt and swarf shall be thoroughly removed by emulsion cleaning.

Rust and scale shall be removed by pickling with dilute acid followed by washing with running water, rinsing with slightly alkaline hot water and drying.

After phosphating, thorough rinsing shall be carried out with clean water followed by final rinsing with dilute dichromate solution and even drying.

The phosphate coating shall be followed by the application of two coats of ready mixed stoving type zinc chromate primer. The first coat may be "flash dried" while the second coat shall be stoved.

After application of the two coats of primer finishing synthetic enamel paint shall be applied, each coat followed by stoving. The second finishing coat shall be applied after completion of tests.

The final finished thickness of paint film on steel shall not be less than 100 microns and shall not be more than 150 microns.

Finished painted surface of panels shall present an aesthetically pleasing appearance free from dents and uneven surface.

A small quantity of finishing paint shall be supplied for minor touching up required at site after the installation of the panels.

Bins and Printed Circuit Cards

Individual bins shall be mounted on a swing able frame so that the connections at the rear are also accessible.

Self retaining thumb head screws shall be needed for holding the bins in position.

Adequate number of card/bin extenders for testing of PCBs shall be provided, each with flexible cables at least two metres long. These extenders shall be of a universal type suitable for use with any card / bin as the case may be.

All adjustments which are to be made while changing a card shall be outside in a separate module preferably plugged into the regulator bin .

Locking of individual cards in a bin shall preferably be through self retaining thumb-head screws.

Control modules shall be in the form of plug in packages, plugged into a module bin. Each plug in unit shall consist of a strong frame on which a printed circuit board would be permanently screwed.

The plug connections shall only be of the pin type.

The printed circuit board (P.C.B.) shall be made of glass fibre filled with epoxy laminates. The plug in unit shall be screwed to the basic socket in the module bin with long through bolts and knurled heads.

The front plates of the plug in unit shall have the switches, the potentiometers, miniature monitoring meters, test points etc. Each plug in unit shall have its own identification legend.

All plug in units shall be polarised to prevent incorrect insertions into the module bin.

The gap between two plug in units inside a bin shall be sufficient to permit adequate ventilation.

The copper side of the printed circuit board shall be lacquered to prevent oxidation.

Each side of the printed circuit board shall have a shield cover to prevent inter circuit and external interference.

The P.C.B. shall be mounted on P.C.B. guides fixed on standard racks and the shield properly grounded.

Control circuit test points shall be easily accessible for monitoring and maintenance.

Annunciation

The annunciator shall work on DC power supply.

Each annunciator window shall have two lamps connected in parallel which operate at not more than 75% of their rated voltage.

Window shall be arranged in a logical group.

The annunciator shall have a module construction with glass epoxy plug in cards.

Alarm bell/siren shall be continuously rated and shall have a series resistance.

The annunciator shall have the following facilities.

a) First in sequence, memory reset.
b) Fleeting faults shall be memorised.
c) Test Feature.

There shall be a three tier system of protection and annunciation:

a) Alarm both audible and visual.
b) Warning with delayed shut down –time delay through a timer of range 0-60 sec.
c) Disturbance associated with failures of systems elsewhere.

Meters

Individual meters shall be provided for speed reference, speed feed back, current reference, current feedback, pulse output, and regulated power supply voltages.

All meters shall be identical and fed through individual buffer I.C. amplifiers.

All meters shall be the circular scale type having a full scale deflection of 2700.

All meters shall conform to at least accuracy class 1.0

All meters with their individual buffer amplifier cards shall be housed in separate bin. It is recommended that the buffer amplifiers all be housed on a single/two card/s and this card/s be itself/themselves housed in the regulator bin.

Sensitive signal leads in that case will not have to traverse from one bin to another, only noise insensitive buffer amplifier output leads will need to go to the meter bin.

Selector switches if used with any meters shall have pistol grip handles.

Wiring

Stranded, flexible copper cable of 2.5 sq.mm shall be used for C.T. circuits and 1.5 sq.mm for other control circuits. However for PCB terminals 0.75 sq.mm may be accepted.

Ultra flexible cables shall be used for all connections from a fixed part to a movable member. In addition, a hanging loop of sufficient length shall be provided to avoid any cable stressing.

All terminal boards for outgoing connections shall be at a height of at least 250 mm from the cubicle floor, and preferably tilted at an angle of 450 to the horizontal for ease of connections. Similarly, connection of the incoming power cables to the bus bars shall be done at a height of at least 250 mm from the cubicle floor.

Item designation and location marking shall be in line with IEC recommendations.

Device labeling shall be on its fixed mounting and not on the device itself such that labeling remains even when the device is replaced. Metallic labels/paper labels or sticker shall be accepted.

2.6 Non-Segregated Bus Duct

2.6.1 Bus Enclosure

- The enclosure shall be made of steel or aluminium alloy,the grade of steel or aluminium alloy.
- The entire bus duct shall be designed for indoor/outdoor installation , with a dust and vermin-proof construction. Bus duct installations meant for outdoor application shall be of weather proof construction and shall have degree of protection better than or equal to IP-55. Outdoor portion of bus duct shall be provided with rain hood.
- The inside of the bus enclosure shall be treated with a matt paint of dark colour, preferably black to facilitate efficient heat dissipation. The bare enclosure with above painting shall be designed so as not to exceed the temperature specified in IS:8084.
- Joints consisting of metallic expansion bellows shall be provided on the bus enclosure at following points :

23 At terminations at transformers
24 At terminations at switchgear cubicles
25 In the run of the bus duct in case of long lengths as required.

- Flexible expansion joints for the enclosure shall be provided wherever deemed necessary. The flexible joints shall take care of expansion and contraction due to temperature variations and fault conditions.
- Necessary bonding shall be provided at the above expansion joints if joints are made of insulating material.
- Three-phase terminal enclosures shall be provided with flanged ends with drilling dimensions to suit the flange at equipment terminals.
- The flanges shall be provided with gaskets, nuts, bolts etc.
- Provision shall be made for periodic inspection of insulators by means of inspection covers. The inspection covers shall be provided at the bottom with quick-acting stainless steel clamps and shall have gaskets. There shall be no joints or fixing bolts on the top surface through which water could seep through.

- The drain plugs shall be easily removable for cleaning purposes.
- The gasket material and thickness shall be so selected as to satisfy the operating conditions imposed by temperature, weathering, durability, etc. Care shall be exercised to ensure that covers fit easily, that the required compression of the gaskets can be obtained without damage to the inspection covers by bolts and that covers do not bend after this compression has been applied. Over-compression of the gaskets shall be avoided.
- The material of the gasket shall preferably be neoprene closed-cell sponge rubber or equivalent.
- Flange gaskets shall be provided at the equipment terminal connections.
- The bus duct shall not have any through bolts. All nuts and bolts shall be mild steel hot dip galvanised. GS spring washers shall be provided for making satisfactory joints. Clamps, splice plates etc. shall be provided wherever necessary.
- Whenever the outdoor portion of the bus duct is of flanged construction but of bolted type a continuous hood made of non-magnetic material shall be provided over the entire length of the outdoor portion of the bus duct to prevent ingress of water particles due to heavy rain fall directly on bus duct enclosure. This hood shall be mounted on bus duct supporting structures and all hardware and accessories required for mounting the hood shall be included in scope of supply.

2.6.2 Bus Conductor

- The material of the conductor shall be of aluminium alloy.
- The temperature rise of conductor shall be as per IS:8084. Also the temperature of the bus shall not exceed 250˚C while carrying the specified short circuit current for one second when a fault occurs at the operating temperature.
- The bus conductor shall be given a coat of matt black paint to facilitate heat dissipation. The bare conductor with above painting shall be designed to carry the normal rated current without exceeding temperature rise as specified in IS:8084
- Flexible aluminium connectors welded to the main busbars shall be provided wherever deemed necessary.

- The connectors shall be of the same material as the conductor and joints shall be silver-plated to ensure an efficient connection. The bolting schedule and contact pressure shall conform to accepted codes of practice.
- Flexible braided copper connections shall be provided at the equipment terminal connections. Bimetallic connectors shall be provided between the busbar and the copper flexible if the bus conductor is of aluminium alloy. The joints shall be capable of 25 mm settlement of the equipment mounting pads. The joints shall be suitably designed to take care of the vibration at the terminals as well as the expansion and contraction of the busbars.
- Expansion joints made of aluminium strips shall be provided wherever deemed necessary, to take care of expansion and contraction of the busbars under normal operating conditions.
- All the above joints shall be tested for temperature rise to prove the adequacy of the design. The maximum temperature rise at the joints shall be less than the specified temperature rise for the busbars.
- The busbar clamps at insulators shall be designed to withstand the forces due to momentary short circuit current. They shall permit free longitudinal movement of the bus bars during expansion and contraction. The material of the clamps shall be aluminium alloy. Suitable aluminium spacers shall be provided wherever necessary.
- All bolts, nuts and lock washers used in the bus assembly shall be of high tensile steel, plated for corrosion resistance. Spring washers of "Beleville" type or equivalent shall be used.
- Suitable splice plates and bimetallic connectors shall be provided wherever necessary.
- Disconnecting links with rating same as that of the main busbars shall be provided in the run of the bus duct to facilitate disconnection of the busbars during testing and maintenance. The separation of the busbar sections with the bolted links removed shall be sufficient to withstand the rated voltage of the bus duct.
- Shorting jumpers, for the purpose of drying out the equipment before commissioning or for carrying out short circuit test on the equipment, rated for the main bus current shall be supplied for shorting the bus duct at a location, adjacent to the disconnecting links.
- The shorting links shall have drilling dimensions matching those of the main bus disconnecting links. Suitable supporting structures and support insulators for the shorting links if necessary shall also be offered.

2.6.3 Phase Barriers

- In segregated phase bus duct if metal barriers are provided, the material shall be same as that of the bus duct enclosure material.
- Insulated phase barriers, when specified, shall be made of non-hygroscope insulating material such as fibre glass.

2.6.4 Bus Support Insulators

- Within the bus duct the bus shall be mounted and supported on insulators. The insulators shall be mounted on resilient pads provided in the bus enclosure.
- The insulators shall be either porcelain or resin cast.
- For bus ducts with voltage rating upto 1100 Volt, Fibre glass/FRP or equivalent type of non-hygroscope insulating supports are acceptable.

2.6.5 Wall Frame Assembly And Seal – off Bushing

- Wherever the bus duct passes through the plant building wall, from indoors to outdoors, a wall frame assembly with seal-off bushings shall be provided to prevent any leakage of rain water, infiltration of dust and air temperature variations from indoors to outdoors. The wall frame shall be fabricated out of aluminium angles and sheet and shall be suitable for grouting in the wall. It shall be provided with flanges on both sides to receive the bus duct flanges. A suitable size breather shall be provided for the two sections of the busduct between the wall frame assembly.
- The bus duct shall be equipped wherever necessary with seal-off bushings to prevent interchange of air at different temperatures. The seal-off bushings shall be flanged type.
- The insulator for wall frame assembly and seal-off bushings shall be of porcelain. Also the bushings shall be designed for thermal expansion/contraction due to temperature differential for outdoor/indoor use.

2.6.6 Bus Duct Supports

- The supporting structure shall be fabricated from standard steel sections and shall be hot dip galvanised after fabrication. The hot dip galvanising shall be in accordance with standards.
- Calculations shall be furnished to substantiate the strength support structure to withstand the various static and dynamic loadings.

- The supporting structures shall include supporting members, brackets, hangers, longitudinal beams, channels, nuts, bolts, washers and all other hardware which are necessary for the erection and support of the entire bus duct installation. All the accessories and hardware of ferrous material shall be hot dip galvanised.
- Studs, nuts, bolts and tapped holes shall conform to the relevant standards. Only hexagonal nuts shall be used. All bolt holes shall be spot faced for nuts.
- Castings and forgings shall conform to respective material specifications and shall be free from flaws. They shall be machined true as per good workshop practice. Welding shall be performed in accordance with relevant recognised standards.
- All threaded pipe connections and fittings, pipe flanges and tube fittings shall comply with relevant standards.
- Indoor portion of the bus duct may be supported from the floor or ceiling beams.
- Outdoor portion of the bus duct shall be supported from ground below on suitable foundation in the ground.
- The foundations and structures in outdoor area shall clear the transformers, transformer foundations, cable trenches.
- Each supporting structure shall be securely connected at two points to the station earthing bus. Earthing of enclosure to support structures shall be securely connected at two ends of busduct. All necessary hardware, such as clamps, connectors, etc. required for this purpose shall be furnished by the BIDDER.

2.7 Cables : ~~HV,~~ LV Power and Control

2.7.1 Applicable Standards

The cables shall conform to the latest applicable standards specified below.

PVC insulated cables	:	IS:694

(for voltage upto 1100 V)		
HRPVC & PVC insulated cables heavy duty	:	IS:1554
Cross linked polyethelen insulated PVC sheathed cables	:	IS:7098
Low frequency cables and wires with PVC insulation and sheath	:	IEC:60189-1 & IEC-60189-2
PVC insulation and sheath of electric cables	:	IS:5831
Polyethylene insulation and sheath for electric cables	:	IS:6474
Conductors for insulated electric cables	:	IS:8130
Methods of test for cables	:	IS:10810
Specification for drums of electric cables	:	IS:10418
Specification for PVC insulated cables for electricity supply	:	BS:6346
Specification for PVC insulation and sheath of electric cables	:	BS:6746

2.7.1 –Features of Construction

(a) XLPE Insulated HV Power Cables :

The Cables shall be 11 kV unearthed grade, heavy duty , stranded aluminium Conductor , XLPE Insulated, Conductor Screening by extruded Semiconducting Compound , insulation screening through Combination of semi conducting compound and non magnetic tape(Copper tape) , inner sheath over laid up cores , galvanised steel wire /strip armoured (Aluminium wire armouring for single core cables) , outer sheath of extruded black PVC Compound type ST-2. Core Identification shall be by printed numerals.

(b) LT Power Cables

(i) PVC Insulated Cables:

The Cables shall be 1.1 KV Grade , heavy duty, Stranded Aluminium / Copper Conductor , PVC Compound type A insulated , inner sheathed, galvanised steel wire /strip armoured ,black PVC compound type ST1 outer sheathed.

(ii) XLPE Insulated Cables:

The Cable shall be 1.1 KV Grade , heavy duty, stranded aluminium/ Copper Conductor , XLPE insulated , inner sheathed, galvanised steel wire / strip armoured ,extruded black PVC Compound type ST2 outer sheathed.

(c) Control Cables:

The Cables shall be 1.1 KV grade, heavy duty, stranded copper conductor, PVC Compound type A Insulated, galvanised steel wire/ strip armoured extruded PVC type ST1 outer sheathed.

2.7.3 Cable Rating

The Contractor shall ensure that cable and wires associated with the distribution and control systems, plant wiring and all other installations throughout the Works are adequately rated for their use.

In assessing the rating of any cable or wire, the following factors shall be taken into account:

Supply voltage and frequency

- Maximum voltage drop permissible
- Type and magnitude of load
- Fault level and duration related to circuit protection relays and fuses
- Circuit overcurrent protection
- Route length and disposition of cables
- Ambient temperature
- Method of installation

All power cables shall be sized for continuous current carrying capacity at the ambient temperature of 45 ^{0}C. The design current of any circuit shall exceed the full load current of the supplied device by at least 10%. Power cables shall be sized to limit the maximum voltage drop to no more than 3 %.

Under motor starting conditions the corresponding voltage drop shall not affect the operation of the motor controls or the ability of the motor to start and run effectively and in any event shall not exceed 10%. The Contractor when sizing cables for the remote operation of shunt trip coils shall take due account of the voltage drop caused by the momentary current surge taken at the instant of energisation. HV and LV cables shall be sized for a fault clearance time of 0.5 seconds for the incoming feeders and 0.16 seconds for switchboard feeders controlled by circuit breaker.

2.7.4 Cable Colours

All cable cores shall be colour coded throughout their length and shall be so connected between switchboard, distribution board, plant and accessories, that the correct sequence or phase colours are preserved throughout the system.

The colour coding should be as follows:

3 phase	red, yellow and blue
single phase or dc	red and black
earth	green/yellow
control	blue (dc), red (ac)

2.7.5 Cable Conductors

Copper conductors shall be used for cables of sizes upto 4 Sqmm .Aluminium conductors shall be used for cables of size 6 Sqmm and above. Cores of cross-sectional area greater than 1.5 mm2 shall be stranded. Lighting final distribution circuits shall be of a minimum cross-section of 1.5 mm2. Power cables shall be of a minimum cross-section of 2.5

mm2.Internal wiring of control panels shall be of a minimum cross-section of 1.0 mm2 flexible and stranded. Control cables shall be of a minimum cross-section 1.5 mm2 for external use and 1.0 mm2 for internal use.

2.7.6 Cable Numbering

All cables shall be allocated a unique number which shall be fixed to each end of the cable using a corrosion resistant label. Cables of different categories shall be tagged with the following subscripts and three digit number.

HV power	HV-P_ _ _
LV power	P_ _ _
Control	C_ _ _
Instrumentation	I_ _ _
Protection	PR_ _ _

2.7.7 Cable Drums

Cables shall be supplied in non-returnable wooden drums. The wood used for construction of the drum shall be properly seasoned and free from defects and wood preservative shall be applied to the entire drum. All ferrous parts shall be treated with a suitable rust preventive coating to avoid rusting during transit or storage.

The Bidder shall indicate in the offer, the maximum length for each size of cable, which can be supplied on one drum. The actual length supplied on each drum shall be within tolerance limit of ± 5% without any tolerance on total ordered quantity of each size of cable. However, before winding the cables on drums. Contractor shall obtain Employer's approval for the drum lengths.

Each drum or coil of cable shall be accompanied by a certificate stating the manufacturer's name, cable size, number of cores, length, result and date of tests as required in the Employer's Requirements. Cables manufactured more than 12 months before delivery will not be accepted. All cables shall be delivered with cable ends effectively sealed by hygroscopic

scaling caps. When a cable is cut from a drum both ends shall be immediately sealed to prevent ingress of moisture. Cables shall not be transported to site in loose coils but a number of short lengths of cable may be transported on the same drum. The Contractor shall be wholly responsible for the purchase and/or hire costs of all cable drums and for the removal of these drums from site after use.

2.7.8 ~~6.12~~ Cable Installation

~~6.12~~2.7.8.1 General

Cables shall be installed in such a way that the minimum bending radii are not reduced when installed or during installation. Cables shall not be installed in ambient temperatures below that recommended by the cable manufacturer.

Cables grouped together shall have insulation capable of withstanding the highest voltage present in the group.

Cables of different categories shall be installed so as to maintain satisfactory clearances for safety and in order to reduce the possibility of electrical interference. The following Table details the distances in mm that shall be maintained between the different categories of cable.

Table of Separation Distances in mm between different Categories of Cable

Cable Category	HV Power	LV Power	C&I/ Protection
~~HV Power~~	~~N/A~~	~~300~~	~~500~~
LV Power	300	N/A	300
C&I/Protection	500	300	N/A

These separations are minimum and special circumstances such as the presence of high current flows, or harmonic content may necessitate larger separation distances.

In order to make economic use of the cable support system, cables shall be arranged in groups of 50 mm maximum overall diameter. These groups shall be securely tied to the cable support system at intervals not exceeding 900 mm for horizontal runs and 300 mm intervals on vertical runs.

Cables shall be laid in a manner such that any electrical interference between cables shall not have a detrimental effect on the life and operation of Plant.

Where practical a separate cable support system shall be provided for power and non-power cables. Where this is not practical a separation of 150 mm shall be maintained between power and non-power cables when run on the same support system.

Heavy duty galvanised iron cable tray and ladder racking shall be used for cable support systems. Plastic or GRP cable support systems shall be used in areas used for the storage and handling of chlorine. These systems shall be used to route cables around walls and within cable trenches. Cables shall be securely fixed to the support systems. Bundling of cables shall be permitted where allowance for this practice has been made in sizing the cables.

2.7.8.2 Cables Laid Direct in Ground

Buried cable up to 650/1 100 V shall have a minimum cover of 500 mm measured to the top of the highest cable. On crossing roadways the cable shall be run through a PVC-U duct of minimum diameter 100 mm with a minimum of 1 000 mm cover and encased on all sides by 150 mm of concrete.

Cables of greater than 650/1 100 V shall be buried with a minimum cover of 1 m.

The bottom of the cable trench shall be freed of sharp stones and such like and 75 mm of sieved sand laid below the cable. After cable laying 75 mm of sieved sand shall be laid above the cable.

Interlocking cable protective covers, minimum 1 m long x 300 mm wide, marked `Danger -Electric Cable' in English and the vernacular shall be laid on top of the sieved sand. Covers shall extend the whole length of the cable trench and shall overlap cables by a minimum of 50 mm.

Warning tape shall be laid a minimum of 200 mm above the protective covers.

Cables are to be installed without tees or through joints unless otherwise approved by the Engineer. Single core cables shall be run in trefoil formation.

2.7.8.3 Cables Laid in Underground Ducts

Underground ducts shall be constructed of impact resistant PVC-U and laid at a minimum depth of 500 mm, ducts shall be surrounded by at least 75 mm of sieved sand except at road crossings where it shall be 1 m deep and encased on all sides by 150 mm of concrete.

The Contractor shall ensure that sufficient draw-in points have been provided and that adequate room has been allowed for installation of cables. Drawstrings shall be provided in all ducts to enable additional cables to be installed when required.

Where cables pass in or out of any duct entries into or within buildings such entries, together with any spare ducts shall be sealed against the ingress of moisture by means of duct stoppers and bituminous compounds or by any other method approved by the Engineer. The stopper shall have a fire resistance of at least 30 minutes. Single core cables in trefoil formation shall pass through the same duct and shall not be separated.

2.7.8.4 Cables installed in Conduit

2.7.8.4.1 General

Conduits shall be galvanised heavy gauge solid drawn or welded screwed steel type and be in accordance with IS 9537 Part 2 or BS 4568. Accessories shall either be malleable cast iron screwed type or pressed steel and galvanised.

A space factor of 40% shall not be exceeded, but in any case conduit of less than 20 mm diameter shall not be permitted. The tubing shall be perfectly smooth inside and out and free from flaws and imperfections of any kind. Both ends of every length of tubing shall be properly reamed with all sharp edges removed before erection.

Where a number of conduits converge, malleable cast iron or heavy gauge sheet steel adaptable boxes shall be employed in order to avoid crossings. Conduits shall be connected by means of male brass bushes and couplings.

Where conduits are greater than 25 mm, straight through joint boxes shall be of the trough type. Where conduit and/or fittings are attached to equipment casings, the material or case of the casing shall be tapped for a depth of not less than 10 mm or male bushes and flanged couplings shall be used.

Heavy hexagonal lock nuts shall be used at all positions where running joints are required and great care shall be taken to ensure that they seat firmly and evenly on to the mating faces of coupling or other adjacent accessories. All junction boxes, draw-in boxes, and inspection fittings, shall be so placed that the cables can be inspected and, if necessary, withdrawn and re-wired throughout the life of the installation.

Generally not more than two bends or offsets or one coupling will be permitted without a suitable inspection accessory. Fish wires shall not be left in conduits after erection. The whole of the installation shall be arranged for a loop-in type of system with joints being carried out at switches, isolators, etc. Intermediate joints in the cable will only be allowed by arrangement with the Engineer. Where terminal blocks are necessary, they shall be of the porcelain type with brass pinching screws.

Ends of conduits which are liable to be left open for any length of time during building operations shall be plugged to prevent the ingress of dirt, cement, etc. and covers, either temporary or permanent, shall be fitted on all boxes.

Generally, conduits shall not cross expansion joints of buildings, but where they cannot be installed in any other manner then a flexible conduit shall be used across the expansion joint. A total 150 mm movement shall be allowed.

2.7.8.4.2 Surface Installation

Surface conduits shall be secured and fixed by means of distance spacing saddles or approved purpose made clips which allow the conduits to be taken directly into accessories without sets or bends. Conduits shall be run in a square and symmetrical manner. An efficient means shall be adopted to provide for the drainage of condensation and the runs shall be properly ventilated. All surface conduit runs shall be marked out for approval by the Engineer before the installation is carried out. Where large multiple parallel conduit runs would occur, use may be made of galvanised cable trunking. Conduits installed on structural steel work shall be secured at

spacingspacings not exceeding those for surface conduit by girder clips, otherwise fixing shall be as for surface conduits on walls, drilled and tapped to the metalwork. Power driven fixings shall only be used with the express permission of the Engineer. Any drilling or access which is required through any structural member of the building shall be agreed with the Engineer before carrying out the work.

Exposed threads and places where galvanising has been damaged shall be cleaned and then painted with two coats of an approved metallic zinc based paint. This treatment shall be applied as the work proceeds.

2.7.8.4.3 Concealed Installation

Concealed conduits shall be securely fixed to prevent movement before laying of screeds, floating of plaster, casting of columns or other building operations necessary after the conduit installation. Crampets or similar fixings shall be used for attaching the conduit to block work, etc. Building nails will not be accepted.

At least 15 mm cover shall be allowed for finishes over the conduit. Where this cover cannot be maintained then expanded metal shall be fitted with the conduit. Conduit cast into reinforced concrete floors shall be fixed to the steel reinforcing with binding wire and the conduit boxes filled with expanded polystyrene or enclosed in a plastic bag to prevent the ingress of concrete when poured. Where possible, the conduit boxes shall be fixed to shuttering to give a flush finish.

Conduit installed in voids, false ceilings, and other concealed routes shall be installed as specified for the surface conduits. Wiring shall be carried out after the false ceiling or permanent ducts have been completed. Conduit installed in floors shall be sealed against ingress of moisture.

The conduit installation shall be inspected by the Engineer before the building operation conceals the work.

2.7.8.4.4 Cable Installed in Flexible Conduit

Flexible conduit shall be of the waterproof galvanised type or PVC wire-wound type with cadmium plated mild steel couplings. Lengths of flexible conduits shall be sufficient to permit withdrawal, adjustment or movement of the

equipment to which it is attached and shall have a minimum length of 300 mm. Flexible conduit shall not be used as a means of providing earth continuity. A single earth conductor of adequate size shall be installed external to the conduit complete with earth terminations.

Where conversion from rigid conduit to flexible metallic conduit is to be made, the rigid conduit shall terminate in a through type box and the flexible conduit shall extend from this box to the equipment, the earth continuity cable shall be secured to the box and to the piece of equipment by properly designed earthing screws. The use of lid facing screws, etc., will not be permitted. Adapters shall incorporate a grub screw or a gland to prevent the flexible conduit becoming loose.

2.7.8.4.5 Cable Installed in Cable Trunking – Metal

Cable trunking shall be manufactured from mild steel of not less than 1.25 mm and shall be hot dipped galvanised. The Contractor shall ensure that the size of the trunking is adequate for the number of cables to be installed together with 50% spare capacity and shall in any case be 50 mm x 50 mm minimum size.

Segregation of cables shall be carried out if required using continuous sheet steel barriers with the bottom edge welded to the trunking.

The trunking shall have two return flanges for rigidity. Where necessary, additional strengthening straps shall be fitted internally. The cover shall overlap the trunking and be made of the same gauge. Fixing screws for covers shall be recessed and be of the self retaining `quick fix' type. All bends, tees and intersections shall be of the gusset type and shall, wherever possible, be purpose made by the manufacturer and of a matching design to the main trunking.

Cables shall be retained in the trunking when the cover is removed by means of straps. Internal connecting sleeves shall be fitted across joints in the trunking and earth continuity ensured by bonding each section of trunking to a continuous earth wire.

Non-flammable fire barriers shall be inserted where the trunking passes through walls or floors. Conduit connections to trunking shall be made by flanged couplings and male bushes.

Trunking shall be supported at intervals not greater than 2 m horizontally or 2.5 m vertically.

Crossings over expansion joints shall be made in flexible conduit.

Should it be necessary to cut or drill a section of trunking or a trunking fitting the bared ends shall immediately be given a coat of zinc rich cold galvanising paint.

Cable and conduit/trunking runs shall be determined by the Contractor and agreed by the Engineer before any work is started. The run shall be at least 150 mm clear of plumbing and mechanical services.

Conduit/trunking systems erected outside a building shall be weatherproof.

2.7.8.4.6 Cable Installed on Cable Tray

Cable tray shall be of perforated sheet steel with formed flanges and of minimum thickness not less than 1 mm for trays up to 100 mm width, not less than 1.25 mm for trays from 100 mm to 150 mm width and not less than 1.5 mm for trays from 150 mm to 300 mm width.

Cable tray shall be hot dipped galvanised. Cable tray for use in areas where chlorine gas may be present shall constructed from U-PVC or GRP. Cable tray supports shall be of a compatible finish with the associated cable tray.

All cable tray tees, intersection units, bends, turns and sets shall, whenever possible, be purpose made by the manufacturer and shall be of a matching design to the main section of cable tray.

Tray shall only be joined by couplers supplied by the manufacturers. The joint shall be secured in accordance with the manufacturers instructions.

Cable tray supports supplied by a manufacturer or made up on Site shall be of ample strength to maintain rigid support to the fully laden cable tray along its entire length and shall ensure that the deflection of any one section does not exceed 15 mm at midspan.

Wherever possible, cable trays shall be installed in full lengths without cutting. Should it be necessary to cut or drill a length of tray, then for galvanised

trays, the bared ends or damaged section of the tray shall immediately be given a coat of zinc rich cold galvanised paint. All site manufactured accessories, supports and metal fittings required to ensure correct installation of the cable trays shall be similarly treated.

All cables shall be firmly secured to the tray using purpose made saddles, as approved by the Engineer, together with proprietary nylon fasteners and/or cable cleats. Following installation of cables, the tray shall remain rigidly supported and the deflection of any section shall not exceed 15 mm at midspan. All brackets and tray work shall be suitable for withstanding a temporary weight of 125 kg.

Cable trays shall not be cut to allow the passage of cables through the surfaces of the tray.

The sizing of the cable tray shall provide a minimum of 25% spare capacity.

The tray shall be run at least 150 mm clear of plumbing and mechanical services.

2.7.8.4.7 Cable Installed on Ladder Rack Systems

Ladder racking either light or heavy weight shall be proprietary item and installed in accordance with manufacturer's instructions. Bends in the installation shall take account of the minimum bending radii of cables to be installed.

Cables shall be clipped to the ladder rack using clips designed for the system in use and appropriate to the type and size of cable installed.

The sizing of the cable rack system shall provide a minimum of 25% spare capacity.

The ladder racking shall be run at least 150 mm clear of plumbing and mechanical services.

2.7.8.4.8 Cable Clipped Direct

All cable hangers, clips, cleats and saddles shall be of an approved type and appropriate to the type and size of cable installed.

Their spacing shall be such as to ensure a neat appearance and prevent sagging of the cables at all times during their installed life.

2.7.8.4.9 Cable Installed in Internal Floor Trench

2.7.8.4.10 In Shallow trenches (maximum depth 500 mm)

In shallow trenches used for electrical services only, cables may be laid in a neat and orderly manner on the floor of the trench. One layer only shall be allowed. Additional cables shall be installed on the walls of the trench in an approved manner.

Where the trench is shared by other services, cables shall be installed on the walls of the trench in an approved manner.

2.7.8.4.11 All other trenches including walk through service ducts

Cabling shall be installed to the walls of the trench in an approved manner.
Where other services are present the cables shall be segregated from them and wherever possible kept above `cold' wet services. Cables should not be run if at all possible above or in close proximity to `hot' services. The cabling shall be installed in such a manner as to allow access to the other services for normal maintenance without disturbance of the electrical installation.

2.7.9 Cable Terminations and Joints

Power Cable Terminations

Power cables shall be terminated in suitable boxes arranged for bolting to switchgear, motor starters and motors. Cores shall have either crimped lugs or sleeves to match either post terminals or bolted clamp terminals.

Each cable entry into a terminating box shall be made through a suitable gland, which shall have provision for securing the armour where applicable. Where single core glands are required these shall be of the non-magnetic type and the associated box bottom plate, where the core passes through, shall not have a continuous magnetic path.

Adequate provision shall be made to bond the cable armouring to the box and/or switchgear casing of a suitable size to withstand the prospective short circuit fault current of the system, glands shall be fitted with earth bonding tags where intimate screwed contact between gland and cable box is not possible.

Where cable glands are exposed to the weather these shall be protected by heat shrink plastic sleeve or purpose moulded sleeves covering the gland continuously from overall sheath to the gland neck.

Where terminations of multicore type have to be made on to items of Plant which have to be dismantled for maintenance, these shall be made off through glands into an adaptable box containing terminals and flexible single cores taken into the equipment via flexible waterproof plastic covered conduit, and a separate earth core linking the box to the equipment.

Where single core cables are glanded to or pass through cabling plates the gland plate or cabling plate shall be constructed of non-magnetic material.

-Power Cable Joints

Through joints shall only be allowed with the approval of the Engineer. Where such joints are necessary in thermoplastic and elastomeric cables, the cables shall be jointed with epoxy or acrylic resin cold setting compound, which has been premeasured and prepacked ready for use. The boxes shall preferably be of split, moulded plastic type with filling vents for compound. Bonding straps shall be fitted with armour clamps across the joint and inspected by the Engineer prior to filling the box with compound. Wrapped pressure type joints will not be accepted.

—Multi core or Control Cable Terminations

A sufficient number of terminals shall be provided to terminate all cable cores. For control and auxiliary wiring an additional 20% of this number shall be provided as spares.

Not more than one core of internal or external wiring shall be connected on any one terminal. Where duplication of terminal blocks is necessary, purpose-made solid links shall be incorporated in the design of the terminal blocks.

Terminals which remain energised when the main equipment is isolated shall be suitably screened and labelled.

Terminal blocks for different voltages or circuit type shall be segregated into groups and distinctively labelled.

—Cable Fixings

Ties and strapping shall be suitable for securing cable and cable groups to cable tray or ladder. They shall be resistant to chemical and marine corrosion. Plastic coated metal ties used in order to obtain corrosion resistance shall not be acceptable. Nylon ties shall be resistant to the effects of ultra-violet light and shall be self-extinguishing.

Large single cables shall be secured with cable clamps or cable cleats.

–Cable Identification

At each end of each cable, in a uniform and visible position a label shall be fixed on the cable in accordance with the cable schedule. Labels shall be made of PVC and shall be indelibly marked to the approval of the Engineer. The label shall be retained using proprietary nylon strips passing through two fixing holes at either end of the label. If the cable gland is not normally visible, then the label shall be fixed inside the panel by means of screws.

-Cable Glands

Glands shall generally be of the mechanical compression hexagon type. Earth continuity of brass glands shall be assured. This may be achieved by the rigid clamping of the armour within the gland and the intimate contact between the threaded components of the gland and the equipment. Each gland shall be installed complete with proprietary earth tag providing a ready means of connecting a flexible strand or strip earth bond to the gland at any position around the gland in relation to the associated apparatus. Adequate earth continuity shall be assured between the earth tag, the gland and the armour wires of the cable where applicable.

Glands for single core cables shall be constructed from non-magnetic materials.

Each gland shall be installed complete with a proprietary non-ferrous lock-nut to secure the gland body to the equipment where the entry hole is plain, i.e. not tapped.

Where holes for cable entries are not provided it shall be the responsibility of the Contractor to mark out and drill such holes. Burrs and swarf shall be removed, care being taken to ensure that swarf and filings, etc do not enter the equipment.

For non-hazardous areas cable glands in situations where moisture may be present shall be double seal weatherproof type, gland shrouds shall be used and entry shall be sealed.

For dry indoor situations, standard industrial glands with shrouds are acceptable.

For hazardous areas, glands conforming to EExd standard shall be used with double seal and shroud.

Power cable glanding arrangements in hazardous areas shall incorporate an insulated adapter and earth link. This shall provide the facility to disconnect the armouring from the glanded device in order that a true earth loop value may be measured when carrying out tests on the installation.

-Marking Locations of Underground Cables

The location of all underground cables shall be engraved on brass or other non-corrodible plates to be fixed to the exterior surface of all walls of buildings 300 mm above ground level and directly above the point where cables pass through the wall.

In addition concrete marker posts shall be installed at intervals of not more than 50 m at all junctions and changes of direction along the cable route. Such marker posts shall be not less than 200 mm high and of substantial construction. A drawing or sample of a typical marker post shall be submitted for the approval of the Engineer.

The markers shall be marked `electric cable' in English and the vernacular.

2.7.10 Drawings and Data

All Drawings, data, technical particulars ,calculations, detailed literature, catalogues ,
test certificates etc shall be submitted along with the bid/ after award of contract as
specified under, " Bid/Contract Drawings" , Part 3, General Requirements, Volume-2 of Bid Documents .

2.8 Cable Carrier System

2.8.1 General

The cable carrier system covers the supply of cable racks, cable trays and its supporting accessories.

2.8.2 Applicable Standards

Steel for general structural purposes	:	IS:2062
Dimensions for hot rolled steel beam, column channel and angle sections	:	IS:808
Code of practice for use of metal arc welding for general construction in mild steel	:	IS:816
Hot deep galvanising of iron & steel	:	IS:2629
Methods of testing uniformity of coating of zinc coated articles	:	IS:2633
Hot dip zinc coatings on structural steel and other allied products	:	IS:4759

2.8.3 Cable Racks and Trays

(a) Typical cable tray arrangement/trench arrangement/directly buried cable arrangement etc. are shown on dwg. no NMT/BWSSP-II/S1b/ KEN/E/1003, 1004&1005.

(b) Cable racks/trays shall be fabricated from standard structural steel members as indicated in Drawing No. NMT/BWSSP-II/S1b/ KEN/E/1003, 1004&1005.

(c) All cable trays, vertical raceways, cable racks and cable tray supporting structures shall be hot dip galvanised.

2.8.4 Galvanising

Wherever galvanising has been specified, the hot dip process shall be used. The galvanised coating shall be of uniform thickness. Weight of Zinc coatings for various applications shall not be less than those indicated below :

(a) Fabricated Steel

Thickness less than 2 mm, but not less than 1.2 mm	340 gms/sq.m 460 gms/sq.m
Thickness less than 5 mm, but not less than 2 mm	610 gms/sq.m
Thickness 5 mm and over	

(b) Fasteners

Upto nominal size M10	270 gms/sq.m
Over M10	300 gms/sq.m

Galvanising shall be carried out after all drilling, punching, cutting, bending and welding operations have been carried out. Burrs shall be removed before galvanising. Any site modification of galvanised parts should be covered well by zinc rich primer and aluminium paint.

2.8.5 Drawings and Data

All Drawings, data, technical particulars ,calculations, detailed literature, catalogues , test certificates etc shall be submitted along with the bid/ after award of contract as specified under, " Bid/Contract Drawings" , Part 3, General Requirements, Volume-2 of Bid Documents.

2.9

26 Lighting System

26.1 General Requirements

(a) The Lighting system includes the following items.

(i) Lighting fixtures complete with Lamps and accessories

(ii) Lighting system equipment

- Light control switches, receptacle units with control switch units, lighting wires, conduits and other similar items necessary to complete lighting system.
- Lighting fixture supports, street lighting poles and flood light towers
- Main Lighting distribution board, lighting panels.
- Multi core cables for street, boundary and flood lighting .

(b) DC Emergency Lighting shall be provided for Substation room , SCADA room , Switchgear room.

Applicable Standards

The design, manufacture and performance of equipment shall conform to the latest standards specified below.

6.14.2.1 Lighting Fixtures & Accessories

Electrical lighting fittings general and safety requirements	:	IS:1913/ BS:4533
Code of practice for industrial lighting	:	IS:6665
Calculation of co-efficient of utilisation	:	IS:3646 (Part - III)
Industrial lighting fittings with metal Reflectors	:	IS:1777

~~Decorative lighting outfits : IS:5077~~

~~Dust proof electric lighting fittings : IS:4012~~
~~Dust tight electric lighting fittings : IS:4013~~
~~Flood lights : IS:10322/BS:4533~~
~~Luminaires for street lighting : IS:10322 Part 5~~
~~Water tight electric lighting fittings : IS:3553/ BS:4533,5225(I)~~
~~Bayonet lamp holders : IS:1258/BSEN 6118 4IEC:60061~~
~~Edision screw lamp holders : IS:10276/BSEN 60238~~
~~Bi Pin lamp holders for tubular fluorescent lamps : IS:3323~~
~~Starters for fluorescent lamp : IS:2215/BSEN 60155~~
~~Holders for starters for tubular fluorescent : IS:3324/ BSEN 60400~~
~~Lamps~~
~~Ballast for use in fluorescent lighting fittings : IS:1534 (Part 1)/BSEN 60920& 60921~~
~~Transistorised ballast for fluorescent lamps : IS:7027~~
~~Ballast for HP mercury vapour lamp : IS:6616~~
~~Capacitors for use in fluorescent, : IS:1569/ BSEN 61048~~
~~HPMV & LP sodium vapour discharge & 61049 /IEC:60586~~
~~Circuits~~
~~Vitreous enamel reflector for tungsten filament lamp : IS:8017~~
~~Tubular fluorescent lamps : IS:2418 (Part 1) /BSEN 60081 IEC:60081~~

~~High pressure mercury vapour lamps : IS:9900/BS:3677/ IEC:60188~~

~~Tungsten filament general electric lamps : IS:418/IEC:60432~~

~~Cast acrylic sheets for use in Luminaires : IS:7569~~

~~Screwless terminal and electrical connections for lighting fittings : IS:10322~~

~~High pressure sodium vapour lamps : IS:9974~~

~~Emergency lighting units : IS:9583~~

~~Ignition proof enclosures, dust tight for elect. equipment : IS:11005~~

~~Luminaires : IS:10322 (Part I to V)~~

~~6.14.2.2 Lighting System Equipment~~

~~Arrangement for busbars, main connections and auxiliary wiring and marking : IS:5578/ 11353/BS:159~~

~~Enclosed distribution fuse boards and cutouts for voltages not exceeding 1000V : IS:2675/ BSEN 60439~~

~~General requirements for switchgear and control gear for voltages not exceeding 1000 V : IS:13947~~

~~Code of practice - installation and maintenance of switchgear : IS:10118/BS:6423 BS 6626, BS 6867~~

~~Factory built assemblies of switchgear and control gear for voltages upto and including 1000 V AC and 1200 V DC : IS:8623/BS 5486/ IEC:60439~~

~~Miniature air break circuit breakers for AC circuits : IS:8828/ BSEN 60898~~

~~HRC cartridge fuse links upto 650 V : IS:9224/BS:88/ IEC:60269~~

~~'D' Type fuses : IS:8187~~

Current transformers	:	IS:2705/BS:7626/ IEC:60185
Voltage transformers	:	IS:3156/BS:7625/ IEC:60186
Direct acting electrical indicating Instruments	:	IS:1248/BS:89/ IEC:60051
A.C. electricity meters	:	IS:722/BS 5685
Electrical relays for power system protection	:	IS:3231/BS:142/ IEC:60255
Switches for domestic and similar purposes	:	IS:3854/BS:3676
Three pin plugs and socket outlets	:	IS:1293/BS:546
Boxes for enclosure of electrical accessories	:	IS:5133(1)
Rigid steel conduits for electrical wiring	:	IS:9537/BS:31
Accessories for rigid steel conduits for electrical wiring	:	IS:3837/BS 31
Flexible steel conduits for electrical wiring	:	IS:3480
Rigid non-metallic conduits for electrical installations	:	IS:9537/BS:4607(2)
Fittings for rigid non-metallic conduits	:	IS:3419/BS:4607(2)
PVC insulated cables for working voltages upto and including 1100 V	:	IS:694
Tubular steel poles	:	IS:2713
Specification for copper rods and bars for electrical purposes	:	IS:613
Code of practice for phosphating iron and steel	:	IS:6005/ BS:3189
Fittings for rigid steel conduits for electrical wiring	:	IS:2667

Lighting Fixtures (Luminaires)

Luminaires shall be designed for continuous trouble-free operation without reduction in lamp life or without deterioration of materials and internal wiring. Outdoor fittings shall be weather-proof and rain-proof type.

The Luminaires shall be designed so as to facilitate easy maintenance, including cleaning, replacement of lamps/starters etc.

~~Connections between different components shall be made in such a way that they will not work loose by small vibration.~~

~~For each type of Luminaires the Contractor shall furnish the utilisation factor tables to indicate the proportion of the light emitted by the bare lamps which falls on the working plane.~~

~~All Luminaires shall be supplied complete with lamps suitable for operation on a supply voltage with the variation in supply voltage, frequency and combined voltage and frequency of ±10%, ±5% and ±10% respectively.~~

~~The Luminaires and accessories shall be designed to have low temperature rise. The temperature rise above the ambient temperature shall be as indicated in the relevant Standards.~~

~~Fluorescent type, mercury vapour and sodium vapour type Luminaires shall be complete with accessories like lamps, ballasts, power factor improvement capacitors, starters, re wirable fuse and fuse base. These shall be mounted as far as possible in the luminaire housing only. If these cannot be accommodated integral with the Luminaires then a separate metal enclosed control gear box shall be included to accommodate the control accessories together with a terminal block suitable for loop in, loop out connections. Outdoor type fixtures shall be provided with outdoor type weather proof box.~~

~~Fluorescent type Luminaires with more than one lamp shall be provided with capacitors connected in lead lag circuit for correction of stroboscopic effect.~~

~~Each luminaire shall have a terminal block suitable for loop in, loop out and T-off connection by 250/400 V, 1 core, PVC insulated copper/aluminium conductor wires upto 4 sq.mm in size. In outdoor areas the termination at the luminaire shall be suitable for 1100 V, PVC insulated, copper/aluminium conductor, armoured cables of sizes upto 6 sq.mm conductor. Terminals shall be of stud or clamp type. The internal wiring should be completed by means of standard copper wire of minimum 1 sq.mm size and terminated on the terminal block. Terminal blocks shall be mounted with minimum two fixing screws.~~

~~Mounting facility and conduit knock-outs for the luminaries shall be provided.~~

~~The fixtures provided shall be energy efficient and shall be consuming less power.~~

~~Earthing~~

~~Each luminaire shall be provided with an earthing terminal suitable for connection to the earthing conductor of 12 SWG GI wire.~~

~~Where separate control gear box is provided for housing the accessories the same shall be provided with an earthing terminal suitable for connecting earthing conductor of 12 SWG GI wire.~~

~~All metal or metal enclosed parts of the luminaire/control gear box shall be bonded and connected to the earthing terminal so as to ensure satisfactory earthing continuity.~~

~~Painting/Finish~~

~~All surfaces of the Luminaire/Control gear box housing accessories shall be thoroughly cleaned and degreased. It shall be free from scale, rust, sharp edges and burrs.~~

~~When enamel finish is specified, it shall have a minimum thickness of 2 mils for outside surface and 1.5 mils for inside surface. The finish shall be non-porous and free from blemishes, blisters and fading.~~

~~The luminaire housing shall be stove enameled/epoxy stove enamelled vitreous enamelled or anodised as indicated under various types of fittings.~~

~~The surface shall be scratch resistant and shall show no sign of cracking or flaking when bent through 90 deg. over 1/2" dia. mandrel.~~

~~The finish of the luminaire shall be such that no bright spots are produced either by direct light source or by reflection.~~

~~External control gear box provided for housing accessories shall be painted or galvanised.~~

~~Decorative Luminaires~~

~~6.14.4.1 Fluorescent Luminaires~~

~~These luminaires shall be generally indoor type provided with cold rolled cold annealed (CRCA) sheet steel channel/rail cum reflector housing complete~~

with all electrical control accessories mounted on it. The finish shall be stove enamelled.

Decorative fluorescent type luminaires shall be either open type, provided with translucent white opal acrylic diffusers, polystyrene lens prismatic or square polystyrene louvers.

Luminaires shall be suitable for the number of lamps of specified wattage, direct mounting on ceiling/wall/column pendant mounting or for recess mounting in false ceiling.

Decorative luminaires with mirror optic reflectors shall be of the wide angle dispersion type. Where these luminaires are mounted in control rooms and computer rooms, clip-on type adjustable reflectors which can be attached onto the tube shall be provided to direct the light output in the desired direction. This is mainly to reduce reflection of the light source from TV/monitor screens.

Luminaires mounted recessed in false ceiling shall be with reflector housing and spring loaded fixing arrangement for the diffuser/louver frame. It shall be possible to have access to the lamp and other accessories from below.

Industrial Luminaires

6.14.5.1 Fluorescent Luminaires

The luminaire shall be provided with CRCA sheet steel mounting rail with reflector of minimum 20 SWG thickness and complete with all control accessories mounted on it. The finish shall be vitreous enamelled.

Luminaires shall be suitable for the number of lamps of specified wattage, direct mounting on ceiling/wall/column/pendent mounting.

The distribution of light shall be such that at least 80% of the total luminous flux from the luminaire shall be in the lower hemisphere.

The luminous output of the luminaire with reflector shall not be less than 75% irrespective of type of reflector used.

6.14.5.2 Incandescent/ Mercury Vapour/ Sodium vapour luminaires

6.14.5.3 Bulk Head Luminaire

The luminaire shall be of robust construction, with cast aluminium/vitreous enamelled housing, heat and shock resistant prismatic or clear glass cover fixed with neoprene gaskets for sealing. For mechanical protection to the glass cover, round steel wire guard with vitreous enamelled finish shall be provided.

The luminaire shall be suitable for incandescent lamp upto 150 watts, for direct mounting to ceiling/wall/column and used for general purpose indoor lighting.

6.14.5.4 High and Medium Bay Luminaires

High and medium bay luminaires shall be with cast aluminium housing, anodised aluminium mirror polished reflector canopy with eye bolt for suspension, cooling fins and glass cover.

The luminaire shall be suitable for mercury vapour lamps upto 1000 watts and sodium vapour lamps upto 400 watts. The control gear accessories shall be mounted integral with the luminaire.

High bay luminaires shall be used when the mounting height is above 8 metres while medium bay luminaires shall be used when the mounting height is around 6 to 8 metres.

Flood Light Luminaire

6.14.6.1 General purpose flood light luminaire

Flood light luminaires shall be of weather proof construction with cast aluminium housing, anodised aluminium mirror polished reflector, heat resistant, toughened glass cover and necessary neoprene gaskets to prevent ingress of dust.

The housing shall be supported on a cast iron base and capable of being swivelled in both horizontal and vertical directions and locked in any desired position.

For focussing purposes, knobs, shall be provided along with sector plate indicating the angle in degrees between 0 and 90 deg. in vertical direction.

The Luminaires shall be suitable for single and dual mercury vapour or sodium vapour lamps upto 400 watts, incandescent lamps upto 1000 watts or halogen lamps upto 1000 watts. When mercury vapour or sodium vapour lamps are specified, the same shall be mounted in a separate sheet metal enclosed/cast aluminium weather proof control gear box.

The luminaire shall be provided with cable gland on the canopy in down ward direction for cable connection.

It shall be possible to adjust the lamp position to achieve wide beam, medium beam or narrow beam.

It shall be possible to replace the lamp from the canopy without opening the front glass.

Outdoor Lantern Luminaires

6.14.7.1 Post top Lantern

Post top lantern Luminaires shall be generally outdoor weather proof type for illumination of walkways, gate posts, gardens etc.

The luminaire shall have cast aluminium spigot of 50/60 diameter finished with corrosion proof paint for mounting, opal acrylic or high density polyethylene (HDP) diffuser bowl, complete with integral mounted control gear, neoprene gaskets, earthing terminal etc.

The luminaire shall be suitable upto 200 W incandescent lamp, 125 W mercury vapour lamps or 70 W sodium vapour lamp.

6.14.7.2 Sub-station Lantern

Sub-station lantern shall be generally outdoor weather proof type for illumination of switchyard equipment.

The luminaire shall have cast aluminium housing finished with corrosion proof paint, spigot for mounting on pole, prismatic glass refractor dome to give distribution of light in horizontal plane, anodised aluminium reflector to give light distribution at an angle 20 to 40 degrees, above the horizontal plane, complete with integral mounted control gear, neoprene gaskets, earthing terminal etc.

The Luminaires shall be suitable upto 200 watts incandescent lamp, 125 W mercury vapour lamp or 70 W sodium vapour lamp.

~~Street Lighting Luminaires~~

~~6.14.8.1 Fluorescent Luminaires~~

~~Street lighting fluorescent luminaire shall be outdoor weather proof type for illumination of secondary roads, walkways, peripheral lighting of buildings etc.~~

~~The luminaire shall be of semi-cut off or non-cut off type, with CRCA sheet steel housing, vitreous enamelled, plain or corrugated clear acrylic cover, complete with integral mounted control gear, neoprene gaskets, side pipe entry or top suspension type.~~

~~The luminaire shall be suitable for 1 x 40 watts or 2 x 40 watts fluorescent tubes and for mounting heights upto 4 metres.~~

~~6.14.8.2 Mercury vapour and sodium vapour luminaires~~

~~Street light mercury/sodium vapour luminaires shall be outdoor weather proof type for illumination of main roads, traffic islands etc.~~

~~The luminaire shall be of semi cut off with cast aluminium housing, acrylic or prismatic cover, polished aluminium reflectors, complete with integral mounted control gear, neoprene gaskets and with rear pipe entry.~~

~~The luminaires shall be suitable upto 400 watts mercury or sodium vapour lamps and for mounting heights from 4 metres to 12 metres.~~

~~6.14.8.3 Portable Emergency Light Luminaire~~

~~Emergency light of Installite luminaire shall be indoor type for providing emergency light during failure of normal AC supply.~~

~~The luminaire shall be with CRCA sheet steel enclosure, complete with metallised mirror reflector, leak proof re-chargeable battery rated for two hour discharge, battery charger, charger-on lamp, push button switches, automatic changeover switch/relay, two metre length cord with plug, mounting pads and other accessories required for satisfactory operation of the luminaire.~~

The luminaire shall be suitable for connection to 240 V, 50 Hz single phase supply. On failure of normal A.C. supply the luminaire shall pick up automatically and on restoration of A.C. supply the luminaire shall switch off automatically.

The luminaire shall be suitable for incandescent lamp upto 40 W or fluorescent lamp upto 20 W.

Accessories for Luminaires

6.14.9.1 Reflectors

The reflectors shall be made of CRCA sheet steel/aluminium/silvered glass/chromium plated sheet copper as indicated for above mentioned luminaires.

The thickness of steel/aluminium shall comply with relevant standards. Reflectors made of steel shall have vitreous enamelled finish. Aluminium used for reflectors shall be anodized/epoxy stove enamelled/mirror polished. The finish for the reflector shall be as indicated for above mentioned fittings.

Reflectors shall be free from scratches or blisters and shall have a smooth and glossy surface having an optimum light reflecting coefficient so as to ensure the overall light output specified by the Contractor.

Reflectors shall be readily removable from the housing for cleaning and maintenance without disturbing the lamps and without the use of tools. They shall be securely fixed to the housing by means of positive fastening device of captive type.

6.14.9.2 Lamp/Starter Holders

Lamp holders shall have low contact resistance, shall be resistant to wear and shall be suitable for operation at the specified temperature without deterioration in insulation value. They shall hold the lamps in position under normal condition of shock and vibration met wit under normal installation and use.

Lamp holders for the fluorescent lamps shall be of the spring loaded bi pin rotor type. Live parts of the lamps holder shall not be exposed during insertion or removal of lamp or after the lamp has been taken out. The lamp holder

contacts shall provide adequate pressure on the lamp cap pins when the lamp is in working position.

Lamp holders for incandescent, mercury vapour and sodium vapour lamps shall be of Edison Screw (E.S.) type.

The starter holders shall be so designed that they are mechanically robust and free from any operational difficulties. They shall be capable of withstanding the shocks met within normal transit, installation and use.

6.14.9.3 Ballasts

The ballasts shall be designed to have a long service life and low power loss. The ballasts shall be of the inductive, heavy duty type copper wire wound, filled with thermosetting, insulating, moisture repellent polyester compound filled under pressure or vacuum. Ballasts shall be provided with taps to set the voltage within the range of variation in supply voltage of ±10% of 240 V. End connections and taps shall be brought out to a suitable terminal block rigidly fixed to the ballast enclosure. Ballasts shall be free from hum and such of those which produce hum shall be replaced by Contractor free of cost.

Ballasts shall be mounted using self locking, anti vibration fixings and shall be easy to remove without demounting the fittings. They shall be in dust tight, non combustible enclosures.

Separate ballast for each lamp shall be provided in case of multi lamp luminaires, except in the case of 2 x 20 Watts luminaires.

6.14.9.4 Starters

Starters shall have bimetal electrodes and high mechanical strength. Starters shall be replaceable without disturbing the reflector or lamps and without the use of any tool. Starters shall have brass contacts and radio interference capacitors.

6.14.9.5 Capacitors

The capacitors shall have a constant value of capacitance and shall be connected across the supply of individual lamp circuits.

The capacitors shall be suitable for operation at specified supply voltage conditions and shall have a value of capacitance so as to correct the power

factor of their corresponding lamps circuit to the extent of 0.95 lag or better.

The capacitors shall be hermetically sealed preferably in a metal enclosure to prevent seepage of impregnant and ingress of moisture.

6.14.9.6 Lamps

Lamps shall be capable of withstanding small vibrations and the connections at lead in wires and filaments/electrodes shall not break under such circumstances.

Incandescent lamps

General Lighting Service (GLS) lamps shall be tungsten filament incandescent type. The filament shall be coiled coil type rated for 230/250 volts, Single phase A.C.

Lamps shall be with Edison Screw type metal lamp caps to prevent pilferage.

Lamps shall be milky white for diffused, soft, glare free lighting and rated upto 100 watts.

Fluorescent Lamps

Fluorescent lamps shall be low pressure mercury vapour type with low wattage consumption and high efficiency and longer burning life (about 2500 hours).

Lamps shall be of white light type suitable for operation on 240 V, single phase A.C. in standard lengths of 2, 4 and 5 feet and ratings upto 65 watts.

Lamps shall be provided with features to avoid blackening of lamp ends.

High intensity discharge lamp

These lamps include high pressure mercury vapour lamps and high pressure sodium vapour lamps.

High pressure mercury vapour lamps shall be with quartz discharge tube, internal coated shell, quick restrike time (of within 5 minutes) and with burning life (about 5000 hours) in standard ratings upto 1000 watts.

High pressure sodium vapour lamps shall be with polycrystalline translucent, coated discharge tube, coated shell, quick restrike time (of within 5 minutes) and with burning life (about 10,000 hours) in standard ratings upto 400 watts

~~Lighting System Equipment~~

~~6.14.10.1 Main Lighting Distribution Board and Lighting Panels (AC & DC)~~

~~Constructional Features~~

~~Boards and panels shall be sheet steel enclosed and shall be fully dust and vermin proof, providing a degree of protection of IP 52. Outdoor panels shall in addition be completely weather-proof with a sloping canopy for protection against rain and providing a degree of protection of IP 55. The sheet steel used for frame, frame enclosures, doors, covers and partitions shall be cold rolled 2 mm thick.~~

~~All boards and panels shall be provided with hinged doors for access to equipment. Doors shall be gasketted all round with neoprene gaskets. For the main floor mounted distribution boards with the switch fuse units arranged in tier formation, the hinged door of each unit shall be interlocked so as to prevent opening of the door when the switch is ON and to prevent closing of the switch with the door not fully closed. However, a device for by passing the door interlock shall be provided to enable the operation of the switch with the door open, when necessary, for examination/maintenance. For wall mounting 1 phase ways lighting panels when provided with MCBs, a hinged, latched front door shall be provided with key locking facility and a slotted backelite sheet shall be provided inside. Only the MCBs operating knobs or the fuse cap covers shall project out of the backelite sheet slots for safe operation and neat appearance. Incomer to lighting panels shall be provided with TPN MCB with ELCB.~~

~~All accessible live connections/metals shall be shrouded and it shall be possible to change individual fuses, switches, MCBs from the front of the boards/panels without danger of contact with live metal.~~

~~For floor mounting type distribution boards, adequately sized mounting channels shall be supplied and for wall/column/structure mounting type panels suitable mounting straps shall be provided.~~

~~Adequate interior cabling space and suitable removable cable entry plates shall be provided for top/bottom entry of cables through glands and or conduits as required. Necessary number of glands to suit the specified~~

cable sizes shall be provided. Cable glands shall be screwed on type and made of brass.

Two earthing terminals shall be provided to suit the earthing conductor.

All sheet steel parts shall undergo rust-proofing process which should include degreasing, de-scaling and a recognised phosphating process. The steel works shall then be painted with two coats of Zinc – chromate primer and two coats of final stove-enamelled finish paint of specified colour.

Busbars

Busbars shall be of copper conductor of hard drawn (HD) and high conductivity. Busbars shall be fully insulated by encapsulation in epoxy resin with moulded caps protecting all joints.

Busbars shall be provided with at least the minimum clearances in air as per applicable standards for 500 V, 3 phase system.

Busbars shall be adequately sized for the continuous current rating such that the maximum temperature of the busbars, busbar risers/droppers and contacts does not exceed 85° C under site reference ambient temperature.

The busbars, busbar connections and busbar supports shall have sufficient strength to withstand thermal and electro-mechanical stresses of the fuse/MCB's let through/cut-off current associated with the specified short-circuit level of the system.

Busbar supports shall be made from suitable insulating material such as Hylam sheets, glass reinforced moulded plastic materials, permali wood or cast resin. Separate supports shall be provided for each phase of the busbars. If a common support is provided for all three phases, anti-tracking barriers shall be incorporated.

The neutral bus of the main 3 phase, 4 wire distribution board shall be rated not less than 50% of the phase busbars. The neutral bus of the 1 phase ways lighting panel shall be rated same as the phase busbars. The neutral bus should have sufficient terminals and detachable links for full number of single-phase outgoing lighting circuits.

6.14.10.2 Panels/Boards' Component Equipment

Switches/Miniature Circuit Breakers (MCB)

~~Switches/MCBs shall be hand operated, air break, quick make, quick break type conforming to applicable standards.~~

~~The switch shall be protected by fuse and the MCB shall be provided with overload/short circuit protective device for protection under overload and short circuit conditions. The minimum breaking capacity of MCBs shall be 6 kA r.m.s. at 415 V/220 V D.C.~~

~~Switch shall have provision for locking in both fully open and closed positions. MCBs shall be provided with locking facility.~~

~~The connections between switch and fuse shall be insulated and all live connections shall be shrouded.~~

~~Fuses~~

~~Fuses generally shall be of the HRC cartridge fuse-link type having a certified rupturing capacity of 80 kA at 440 V. Fuses upto 63A for distribution systems of medium short circuit levels may be of HRC cartridge screw cap, D type, having a certified rupturing capacity of not less than 46 kA at 440 V and 16 kA at 250 V D.C.~~

~~Fuses shall be provided with visible indication to show that they have operated.~~

~~Cartridge fuses shall preferably be mounted in moulded plastic carriers. If fuse carriers are not provided, insulated fuse pulling handle shall be provided for each size of fuse for each switchboard.~~

~~Indicating Instruments and Meters~~

~~Whenever required, instruments and meters shall be of the flush mounting type. They shall be suitably mounted so as to provide for easy access to CTs and small wiring.~~

~~Instruments shall be of minimum 96 mm square size, shall have provision for zero adjustment outside the cover and black numerals on white dial.~~

~~Watt hour meters shall be of direct reading electro dynamometer type complete with cyclometer type dials and reverse running stops.~~

~~Ammeter/Voltmeter selector switches having 3 positions and off, with stay put contacts rated 10A shall be provided when specified.~~

~~Potential fuses shall be provided at the tap-off point from the busbars for the voltmeters.~~

~~Instrument Transformers~~

~~Current and voltage transformers shall be of the dry type, of metering accuracy class 1.0. Unless otherwise specified, it shall be the responsibility of the Contractor to ensure that the VA burden of the instrument transformer is adequate for the meters connected to it.~~

~~Test links shall be provided in both secondaryleads of the CTs to easily carry out current and phase angle measurement tests. Facilities shall be provided for short-circuiting and grounding the CTs at the terminal blocks.~~

~~Voltage transformers shall be provided with suitably rated primary and secondary fuses.~~

~~Indicating Lamps~~

~~Indicating lamps shall be of the filament type and low watt consumption.~~

~~Lamps shall be provided with series resistors.~~

~~Internal Wiring~~

~~Panels/boards shall be supplied completely wired, ready for the external connections at the terminal blocks. Wiring shall be carried out with 650/1100V grade, PVC insulated, stranded aluminium/copper conductors. Conductors of adequate sizes shall be used to suit the rated circuit current.~~

~~Engraved identification ferrules, marked to correspond with the wiring diagram shall be fitted at both ends of each wire.~~

~~All wiring shall be terminated on terminal blocks. Terminal blocks shall be one piece moulded rated 500 V, of reputed make, preferably stud type for higher current ratings such that wires are connected by cable lugs and complete with nuts and washers. Terminals shall be adequately rated for the circuit current, the minimum rating shall be 20 A.~~

~~Terminals for circuits with voltage exceeding 125 V shall be shrouded.~~

~~Terminals shall be numbered and provided with identification strip for identification of the circuit.~~

~~Terminal blocks for C.T. secondary lead wires shall be provided with shorting and disconnecting/earthing facilities.~~

~~6.14.10.3 Labels & Diagram Plate~~

All door mounted equipment as well as equipment mounted inside the switchboard/panels shall be provided with individual labels with equipment designation/rating. Also the boards/panels shall be provided on the front with a label engraved with the designation of the board/panel.

Labels shall be made of non rusting metal, 3-ply lamicoid or engraved PVC

Inside the door of the 1 phase ways lighting panels a circuit diagram/description shall be fixed for reference and identification.

6.14.10.4 Light Control Switches

Light control switches of ratings and types, i.e. decorative/industrial shall be supplied as required. The switches shall be suitable for use on 240 V, 1 Ph, 50 Hz supply.

Switches shall be of flush type for mounting behind an insulated plate or incorporated with a switch plate for mounting flush with the surface of wall or switch box/suitable enclosure. The switch box/enclosure may be recessed into or mounted on a wall as per the requirement of project layouts.

The size of enclosure boxes shall be chosen to accommodate the number of switches to be installed at the particular location. The enclosures shall be 18 gauge sheet steel galvanised. The enclosure box shall be covered with perspex/insulating cover. An enclosure intended for surface mounting shall not have holes or gaps in its sides other than those expressly provided for cable entry.

6.14.10.5 Receptacle Units

Receptacle units shall consist of socket outlet with associated switch and plug. The socket outlet and switch or MCB shall be flush mounted within galvanised 18 gauge steel enclosure with insulation cover. The box may be recessed into or mounted on a wall as per requirements of project layouts.

The receptacle units shall be suitable for 240 V, 1 ph - N, 50 Hz/415 V, 3 Ph - N, 50 Hz supply as required.

Single phase receptacles shall be associated with a switch/MCB of same current rating and the receptacle shall become live only when the associated switch/MCB is in "ON" position.

Three phase receptacles shall be associated with a TPN switch housed in the same enclosure. The receptacle shall become live only when the associated switch is in "ON" position.

The plugs shall be provided with cord grips to prevent strain and damage to conductors/wires at connection and entry points.

6.14.10.6 Lighting Wires

The wires for wiring in lighting system shall be 250/440 V, 1/C, PVC insulated, unarmoured with stranded copper conductors.

The minimum area of conductors shall be 1.5 sq.mm. for light fittings and 5A Receptacles and 2.5 sq.mm for receptacles rated 15 A and above.

The wires shall be coaded white for phase/positive of D.C. and black for neutral/negative of D.C.

6.14.10.7 Conduits

Rigid steel/non-metallic conduits and their associated fittings as required shall conform to applicable standards. The minimum size of conduit shall be 20 mm for surface installation and 25 mm for concealed installation.

Steel conduits shall be seamed by welding and hot dip galvanised. They shall be supplied in standard lengths of 5 m.

Supply of conduits shall include all associated fittings like couplers, bends and tees as required for lighting system installation work.

6.14.10.8 Junction Boxes

Junction boxes with terminals shall be supplied for branching and terminating lighting cables when required for outdoor areas, 3 phase receptacles etc.

The junction boxes shall be dust and vermin proof and shall be fabricated from 14 gauge sheet steel and shall be complete with removable cover plate with gaskets, two earthing terminals each with nut, bolt and washer. Boxes shall be additionally weather proof.

The boxes shall have provision for wall, column, pole or structure mounting and shall be provided with cable/conduit entry knock outs, terminal blocks, HRC fuses as required.

The terminal blocks, with specified number of terminals, shall be mounted securely on brackets welded to the back sheet of the box. The terminals

shall be 600 V, grade, one piece construction complete with terminals, insulation barriers, galvanised nuts, bolts and washers and provided with identification strips of PVC. The terminals shall be made of copper alloy and shall be of box clamp type.

The boxes shall be painted with one shop coat of Red oxide zinc chromate primer followed by a finishing coat of paint.

6.14.10.9 Lighting Poles and Flood Light Pole Mounting

Lighting poles for street lights and flood lights shall be of stepped tubular steel poles construction as per applicable standard. These poles shall be coated with bituminous preservative paint on the inside as well as embedded outside surface. Exposed outside surface shall be painted with one coat of red lead oxide primer. After completion of installation two coats of aluminium paint shall be applied.

Poles for mounting flood lights shall be supplied whenever required and as per typical attached drawing. Unless otherwise specified, poles, shall be painted with red lead oxide primer and two coats of aluminium paint. A steel ladder shall be provided. The length of each step of the ladder shall be at least 300 mm and spacing between two adjacent steps not more than 300 mm.

The supply of poles shall be complete with fixing bracket/necessary pipe reducer for fixing the fitting and also include the necessary associated pole mounted junction boxes. The required sizes of poles and the junction box shall be as indicated in the attached drawings.

6.14.11 Drawings and Data

All Drawings, data, technical particulars ,calculations, detailed literature, catalogues , test certificates etc shall be submitted along with the bid/ after award of contract as specified under " Bid/Contract Drawings" , Part 3, General Requirements, Volume-2 of Bid Documents.

-Earthing and Lightning Protection System

2.9.1 General

The earthing and lightning protection system covers earthing conductors, earth electrodes and accessories. Metallic frame of all electrical equipment shall be earthed by two separate and distinct connections to earthing system , Crane rails , tracks , metal pipes and conduits also shall be earthed at two points . Steel RCC Columns ,metallic stairs and rails of the building housing electrical equipment also shall be connected to nearby earthing grid conductor . Metallic sheaths/ screens and armour of multicore cables shall be earthed at both ends. Metallic sheaths and armour of single core cables shall be earthed at the switchgear end only. Every alternate post of switchyard fence shall be connected to the earth grid by GS flat and gates by flexible lead to earthed post.Each Continuous laid length of cable tray shall be earthed at minimum two places by GS Flats to earthing system , the distance between the earthing points shall not exceed 30m. Lightning Protection System shall compromise vertical / horizontal air terminations , down conductors , test limits and earth electrodes. Air terminations , down conductors and test links shall be of galvanised steel conductors and earth connection below the ground level shall be of mild steel.

Lightning Protection System down conductors shall not be connected to other earthing conductors above the ground level .

2.9.2 -Applicable Standards

The earthing and lightning protection system shall conform to the Indian Electricity rules, and the latest applicable standards indicated below :

Code of Practice for Earthing	:	IS:3043
Code of Practice for the Protection of Building and allied structure against lightning	:	IS:2309

Hot dip galvanising	:	IS:2629, 2633, 4759
Structural steel	:	IS:2062 & 808
Welding	:	IS:816

2.9.3 –Earthing Conductor

The electrical installation shall where required be connected to the general mass of the earth by an earthing conductor. The material used for the earthing conductor shall be as follows:

(a) conductors above ground shall be galvanised steel flat ;

(b) conductor buried in the ground or embedded in concrete shall be mild steel, rod /flat .Allowance shall be made for reduction in the cross section of the steel over the design life of the earthing system;

The earth electrode system shall comprise one or more earth electrodes, earthing network, mesh or a combination of these in order to obtain the required earth electrode resistance.

Earth electrodes where used shall be of heavy duty galvanised mild steel of not less than 40 mm NB and 3000 mm long. Where multiple electrodes are used they shall be separated by a distance of not less than the driven length.

Each earth electrode pipe shall be welded at the top to a mild steel plate to which the earthing tapes shall be connected. These connections shall each be housed in individual concrete inspection chamber set flush to the finished ground level and shall allow disconnection for testing of individual electrodes. The chamber shall be permanently marked `Electrical Earth'.

All materials used for the earth electrode installation shall be purpose made for the application and site conditions and shall be approved by the Employer's Representative.

Unless otherwise stated all excavation for the installation of the earth electrodes and the inspection pit shall be carried out by the Contractor.

After the earth installation has been completed the Contractor shall demonstrate to the Employer's Representative that the resistance of the electrodes to earth and the continuity of the earth network are within the limits specified. Any additional earth electrodes and test instruments required for the tests shall be provided by the Contractor.

Marker posts and plates shall be provided to mark the route of buried tape or conductor electrodes. The markers shall be similar to those provided for cable routes.

The lightning protection shall be provided by the contractor as per code of practice for lightning protection – IS : 2309.

2.9.4 –Main Equipotential Bonding Conductor

Main equipotential bonding conductors shall be provided to connect the earth electrode system to conductive parts forming the Works.

Equipotential bonding conductors shall have the following minimum sizes.

a) Main Equipotential Conductors

- Main Earth Conductor buried in earth — 40 mm dia MS Rod / 50 x10mm GS flat
- Transformers, main switchboard and standby generator installation. — 50 x 10 mm flat
- interconnection to lightning protection system — 50 x 10 mm flat
- interconnection to MCC s — 50 x 10 mm /50 x6mm flat

b) Equipotential Conductors

- interconnection to CP s	25 x 3 mm	flat
- power factor correction capacitor panel	25 x 3 mm	flat
- local push buttons	14 SWG	wire
- lighting distribution board	4 SWG	wire
- lighting and receptacle system	12 SWG	wire
- outdoor street lighting wire	8 SWG	
- ladder rack and cable tray at suitable points	25 x 3 mm	flat
- hand rails and metallic structures	25 x 3 mm	flat
- building reinforcement	25 x 3 mm	flat
- incoming and outgoing process services	25 x 3 mm	flat
- steel structures comprising storage tanks, mezzanine platform, crane rails, air handling ductwork systems etc.	25 x 3 mm	flat
- LV Motors		
- up to 10 kW	8 SWG	wire
- 10 to 20 kW	4 SWG	wire
- 20 to 50 kW	25 x 3 mm	flat
- Earth electrode	40mm dia 3000 mm long heavy Duty G.I. pipe electrode	

Notes :

1 Equipotential conductors shall interconnect between the device to be bonded and the main equi-potential conductor.

2 Connections to building structural steel work or concrete reinforcement shall be made by a bolted connection to a tag welded to the steel work or reinforcement bars. Unless otherwise specified at least two connections shall be made to the steel work and reinforcement bars at the perimeter of each building at diagonally opposite locations.

2.9.5 Circuit Protective Conductors

An independent circuit protective conductor shall be provided for each circuit and may comprise one or any of the following as appropriate:

- a separate core within a multicore cable;
- a separate conductor installed within a conduit or trunking. Steel conduit or trunking shall not be used as a circuit protective conductor;
- the metal sheath of an armoured cable. The sheath shall be bonded to the metalwork of the apparatus and to the apparatus earth bar if any;
- the copper sheath of a mineral insulated copper sheathed cable;
- an independent earthing conductor MS or GS conductor run adjacent to the circuit it protects.

Circuit protective conductors associated with the main circuits supplying switchboards and large electrical loads, i.e. motors in excess of 75 kW shall form a separate core of a multicore cable feeding the device or shall be an independent insulated copper conductor run adjacent to the supply cable. The size of the circuit protective conductor shall be calculated in such a manner as not to take into consideration the contribution of any other parallel or fortuitous earth paths.

The armouring of the supply cable shall not form the sole means of earthing a switchboard or large electrical load.

Where the cable armouring or sheath is used as the circuit protective conductor it shall be securely bonded at both ends to the metalwork of the apparatus and to an earth bar. Particular care shall be taken to ensure continuity across items of apparatus situated within a cable run and should the design of such items of apparatus not give adequate and lasting continuity through its structural body then additional earthing clips and conductors shall be provided to independently bond the cable sheaths together. Similarly additional earthing clips shall be provided to bond the cable sheaths/armour to any piece of apparatus fitted with a special earth terminal should the earth connection for the termination gland be

inadequate. Any additional earthing clips shall be fitted within the apparatus wherever possible.

2.9.6 –Instrumentation Earth

An instrumentation earth bus, if required shall be provided in each control panel. This shall comprise a copper flat of cross section not less than 25 x 6 mm and length to suit the number of connections. It shall be mounted on at least two insulated supports and be provided with a single earth connection to the instrument earth. If due to the physical size of a control panel more than one instrument earth bar is required the additional bar shall be connected again with a single earth connection to the same point as before. In this fashion all instrument earths shall be connected radially from the same earth point.

The earth pit for instrumentation system shall be separate. Electric earth pit shall not be used for earthing of instrumentation equipment. All signal cable screens (analogue and digital) shall be terminated onto the instrument earth bar. Signal cable screens shall be earthed at the control panel end only. Screens at the field end shall be tied back and insulated.

SPD s associated with the control and instrumentation system shall be earthed to the instrument earth in accordance with the SPD manufacturers recommendations.

2.9.7 Galvanising

Wherever galvanising has been specified, the hot dip process shall be used. The galvanised coating shall be of uniform thickness. Weight of Zinc coatings for various applications shall not be less than those indicated below :

a) Fabricated Steel

Thickness less than 2 mm,	340 gms/sq.m
But not less than 1.2 mm	460 gms/sq. M
Thickness less than 5 mm, but not less than 2 mm	610 gm / sq.m
Thickness 5 mm and over	

b) Fasteners

	270 gms/sq.m
Upto nominal size M10	300 gms/sq.m
Over M10	

Burrs shall be removed before galvanising. Any site modification of galvanised parts should be covered well by zinc rich primer and aluminium paint.

2.10

27 ~~P~~Preferred Makes/ Manufacturers:

List of preferred makes for Electrical Equipment / Items:

SL NO	DESCRIPTION	VENDOR/MANUFACTURER/ MAKE
~~1~~	~~Transformers~~	~~M/s ABB~~ ~~M/s BHEL~~ ~~M/s Siemens~~

SL NO	DESCRIPTION	VENDOR/MANUFACTURER/ MAKE
		~~M/s Areva T&D~~ ~~M/s Crompton Greaves Limited~~ ~~M/S Volt Amp~~ ~~M/S Bharat Bijlee~~ ~~M/s Kirloskar Electric~~ ~~M/s EMCO~~
~~2~~1	~~11 kV~~ 415 LT Metal enclosed switchboards	M/s Siemens M/s ABB ~~M/s Crompton Greaves Limited~~ ~~M/s Areva~~ ~~M/s BHEL~~ M/s Schneider Electric ~~M/s Kiroloskar Electric~~
3	Protective Relays	M/s ABB M/s Schneider Electric M/s L&T M/s GE M/s Siemens ~~M/s Areva T&D~~ M/s Easun Reyrolle
4	Current Transformers	M/s ABB ~~M/s Areva T&D~~ M/s Siemens ~~M/s CGL~~ M/s Kappa M/s Ind Coil
5	Voltage Transformers	M/s ABB ~~M/s Areva T&D~~ M/s Siemens M/s CGL

SL NO	DESCRIPTION	VENDOR/MANUFACTURER/ MAKE
		M/s Kappa M/s Ind Coil
6	PCC's/MCC's/PDB's/ LV Switchgears& Control gears	M/s Schneider Electric M/s ABB M/s. Siemens M/s GE M/s L&T
~~7~~	~~L.T Power Capacitors~~	~~M/s BHEL~~ ~~M/s ABB,~~ ~~M/s CG Power Systems~~ ~~M/s Universal~~ ~~M/s Madhav~~ ~~M/s Shreem~~ ~~M/s L&T~~
~~8~~	~~Diesel Engines~~	~~M/s Cummins~~ ~~M/s Caterpillar~~ ~~M/s Kirloskar Oil Engines~~
~~9~~	~~Alternators for DG Sets~~	~~M/s Kirloskar Electric~~ ~~M/s CGL~~ ~~M/s BHEL~~ ~~M/s Jyoti~~ ~~M/s Stamford~~
10	Variable Frequency Drives	M/s Siemens M/s ABB M/s Schneider Electric M/s L&T M/s.Bharat Bijlee
~~13~~	~~Batteries~~	~~M/s Exide Industries~~ ~~M/s AMCO~~

SL NO	DESCRIPTION	VENDOR/MANUFACTURER/ MAKE
		~~M/s HBL-NIFE~~
~~14~~	~~Battery Chargers~~	~~M/s Universal Instruments~~ ~~M/s Amararaja~~ ~~M/s Chabhi Electricals~~ ~~M/s HBL-NIFE~~ ~~M/s Caldyne~~
~~15~~	~~Lighting Fixtures and Accessories~~	~~M/s Philips~~ ~~M/s ABB~~ ~~M/s Crompton Greaves Limited~~ ~~M/s Wipro~~ ~~M/s Bajaj Electricals~~
16	LT Bus Ducts	M/s Star Drive M/s Power Gear M/s Control &Switchgear
17	Power Cables and Wires	M/s Universal Cables M/s Polycab M/s Havell's M/s CCI M/s Finolex M/s NICCO
18	MLDB's , LDB's, SDB's, MCB's, RCCB's	M/s Havells M/s Standard M/s Legrand M/s L&T M/s Siemens
~~19~~	~~Switches , Plugs,Sockets~~	~~M/s Legrand~~ ~~M/s Havells~~ ~~M/s Anchor~~

SL NO	DESCRIPTION	VENDOR/MANUFACTURER/ MAKE
		~~M/s Cona~~
~~20~~	~~Ceiling Fans~~	~~M/s Havells~~ ~~M/s Crompton~~ ~~M/s Orient~~ ~~M/s Bajaj~~ ~~M/s Usha~~
~~21~~	~~11kV Cable termination~~	~~M/s Reychem~~ ~~M/s Mahindra~~ ~~M/sREPL~~

Note:

Other Makes, if offered, are subject to Specific Approval by the Employer/ Employer's
Representative based on the Submission of the following documents by the bidder:

(i) Copies of Type Test Certificate not older than 5 years for the items offered.

(ii) List of Clients to whom already the items have been supplied along with the the year of Supply and Value of Orders

(iii) Copies of Performance Certificate from the User's for the items.

(iv) Copy of latest ISO Certification for the Manufacturer

(v) Details of Manufacturing Facilities

(vi) Turn Over of the Manufacturer

(vii) Copies of Approval for the items from reputed Consultants.

End of Part 62B